

Description

The SAMB11 is an ultra-low power Bluetooth® SMART (BLE 4.1) System on a Chip with Integrated MCU, Transceiver, Modem, MAC, PA, TR Switch, and Power Management Unit (PMU). It is a standalone Cortex®-M0 applications processor with embedded Flash memory and BLE connectivity.

The qualified Bluetooth Smart protocol stack is stored in dedicated ROM, the firmware includes L2CAP service layer protocols, Security Manager, Attribute protocol (ATT), Generic Attribute Profile (GATT) and the Generic Access Profile (GAP). Additionally, application profiles such as Proximity, Thermometer, Heart Rate, Blood Pressure, and many others are supported and included in the protocol stack.

Features

- Complies with Bluetooth® V4.1, ETSI EN 300 328 and EN 300 440 Class 2, FCC CFR47 Part 15 and ARIB STD-T66
- 2.4GHz transceiver and Modem
 - -95dBm/ -93dBm programmable receiver sensitivity
 - -20 to +3.5dBm programmable TX output power
 - Integrated T/R switch
 - Single wire antenna connection
- ARM® Cortex®-M0 32-bit processor
 - Single wire Debug (SWD) interface
 - 4-channel DMA controller
 - Brown out detector and Power On Reset
 - Watch Dog Timer
- Memory
 - 128kB embedded RAM (96kB available for application)
 - 128kB embedded ROM
 - 256kB Flash
- Hardware Security Accelerators
 - AES-128
 - SHA-256
- Peripherals
 - 23 digital and 3 wakeup GPIOs with 96kΩ internal pull-up resistors, 4 Mixed Signal GPIO
 - 2x SPI Master/Slave
 - 2x I²C Master/Slave and 1x I²C Slave
 - 2x UART
 - Three-axis quadrature decoder
 - 4x Pulse Width Modulation (PWM), 3 General Purpose Timers, and one Wakeup Timer
 - 4-channel 11-bit ADC

- Clock
 - Integrated 26MHz RC oscillator
 - 26MHz crystal oscillator
 - Integrated 2MHz sleep RC oscillator
 - 32.768kHz RTC crystal oscillator
- Ultra Low power
 - 1.1µA sleep current (8K RAM retention and RTC running)
 - 3.0mA peak TX current (0dBm, 3.6V)
 - 4.0mA peak RX current (3.6V, -93dBm sensitivity)
- Integrated Power management
 - 2.3-4.3V battery voltage range (limited by Flash memory)
 - Fully integrated Buck DC/DC converter
- Bluetooth SIG Certification –
 - The ATSAMB11 uses the ATBTLC1000 as its Bluetooth controller and is certified under the ATBTLC1000.
 - QD ID Controller (see declaration [D028678](#))
 - QD ID Host (see declaration [D028679](#))

Table of Contents

| | |
|---|-----------|
| Description | 1 |
| Features | 1 |
| Table of Contents | 3 |
| 1 Ordering Information | 5 |
| 2 Package Information | 5 |
| 3 Block Diagram | 6 |
| 4 Pinout Information | 7 |
| 5 Package drawing | 10 |
| 6 Power Management | 11 |
| 6.1 Power Architecture | 11 |
| 6.2 DC/DC Converter..... | 12 |
| 6.3 Power Consumption..... | 13 |
| 6.3.1 Description of Device States..... | 13 |
| 6.3.2 Controlling the Device States..... | 14 |
| 6.3.3 Current Consumption in Various Device States..... | 14 |
| 6.4 Power-Up Sequence..... | 15 |
| 6.5 Power On Reset (POR) and Brown Out Detector (BOD) | 16 |
| 7 Clocking | 18 |
| 7.1 Overview..... | 18 |
| 7.2 26MHz Crystal Oscillator (XO)..... | 19 |
| 7.3 32.768kHz RTC Crystal Oscillator (RTC XO) | 20 |
| 7.3.1 General Information | 20 |
| 7.3.2 RTC XO Design and Interface Specification | 23 |
| 7.3.3 RTC Characterization with Gm Code Variation at Supply 1.2V and Temp.=25°C | 23 |
| 7.3.4 RTC Characterization with Supply Variation and Temp.=25°C..... | 24 |
| 7.4 2MHz and 26MHz Integrated RC Oscillator | 25 |
| 8 CPU and Memory Subsystem | 27 |
| 8.1 ARM Subsystem | 27 |
| 8.1.1 Features..... | 27 |
| 8.1.2 Module Descriptions | 28 |
| 8.2 Memory Subsystem | 29 |
| 8.2.1 Shared Instruction and Data Memory | 29 |
| 8.2.2 ROM | 30 |
| 8.2.3 BLE Retention Memory..... | 30 |
| 8.3 Non-Volatile Memory | 30 |
| 8.4 Flash Memory | 30 |
| 9 Bluetooth Low Energy (BLE) Subsystem | 32 |
| 9.1 BLE Core | 32 |
| 9.1.1 Features..... | 32 |
| 9.2 BLE Radio..... | 32 |
| 9.2.1 Receiver Performance | 32 |

| | | |
|-----------|--|-----------|
| 9.2.2 | Transmitter Performance | 33 |
| 9.3 | Atmel Bluetooth SmartConnect Stack..... | 33 |
| 10 | External Interfaces | 35 |
| 10.1 | Overview..... | 35 |
| 10.2 | I ² C Master/Slave Interface | 37 |
| 10.2.1 | Description..... | 37 |
| 10.2.2 | I ² C Interface Timing | 38 |
| 10.3 | SPI Master/Slave Interface | 39 |
| 10.3.1 | Description..... | 39 |
| 10.3.2 | SPI Interface Modes | 40 |
| 10.3.3 | SPI Slave Timing | 41 |
| 10.3.4 | SPI Master Timing | 42 |
| 10.4 | UART Interface | 42 |
| 10.5 | GPIOs..... | 43 |
| 10.6 | Analog to Digital Converter (ADC) | 43 |
| 10.6.1 | Overview..... | 43 |
| 10.6.2 | Timing..... | 44 |
| 10.6.3 | Performance | 44 |
| 10.7 | Software Programmable Timer and Pulse Width Modulator | 48 |
| 10.8 | Clock Output..... | 48 |
| 10.8.1 | Variable Frequency Clock Output Using Fractional Divider | 48 |
| 10.8.2 | Fixed Frequency Clock Output | 48 |
| 10.9 | Three-Axis Quadrature Decoder..... | 49 |
| 11 | Reference Design | 50 |
| 12 | Bill of Material (BOM) | 51 |
| 13 | Electrical Characteristics | 52 |
| 13.1 | Absolute Maximum Ratings | 52 |
| 13.2 | Recommended Operating Conditions | 52 |
| 13.3 | DC Characteristics..... | 53 |
| 14 | Errata..... | 54 |
| 15 | Document Revision History | 55 |

1 Ordering Information

| Ordering Code | Package | Description |
|-------------------|--------------|-------------------|
| ATSAMB11G18A-MU-T | 6x6mm QFN 48 | SAMB11Tape & Reel |
| ATSAMB11G18A-MU-Y | 6x6mm QFN 48 | SAMB11 Tray |


2 Package Information

Table 2-1. SAMB11 6x6 QFN 48 Package Information

| Parameter | Value | Units | Tolerance |
|------------------|---------|-------|-----------------|
| Package Size | 6x6 | mm | ± 0.1 mm |
| QFN Pad Count | 48 | | |
| Total Thickness | 0.85 | mm | +0.15 /- 0.05mm |
| QFN Pad Pitch | 0.4 | | |
| Pad Width | 0.2 | | |
| Exposed Pad size | 4.2x4.2 | | |

3 Block Diagram

Figure 3-1. SAMB11 Block Diagram



4 Pinout Information

SAMB11 is offered in an exposed pad 48-pin QFN package. This package has an exposed paddle that must be connected to the system board ground. The QFN package pin assignment is shown in Figure 4-1. The color shading is used to indicate the pin type as follows:

- Red – analog
- Green – digital I/O (switchable power domain)
- Blue – digital I/O (always-on power domain)
- Yellow – digital I/O power
- Purple – PMU
- Shaded green/red – configurable mixed-signal GPIO (digital/analog)

The SAMB11 pins are described in Table 4-1.

Figure 4-1. SAMB11 Pin Assignment




Table 4-1. SAMB11 Pin Description with Default Peripheral Mapping


| Pin # | Pin Name | Pin Type | Description / Default Function |
|-------|----------------|------------------|---|
| 1 | VDD_VCO | Analog/RF | RF Supply 1.2V |
| 2 | VDD_RF | Analog/RF | RF Supply 1.2V |
| 3 | RFIO | Analog/RF | Rx input and Tx output |
| 4 | VDD_AMS | Analog/RF | AMS Supply 1.2V |
| 5 | LP_GPIO_0 | Digital I/O | SWD Clock |
| 6 | LP_GPIO_1 | Digital I/O | SWD I/O |
| 7 | LP_GPIO_2 | Digital I/O | UART1 RXD |
| 8 | LP_GPIO_3 | Digital I/O | UART1 TXD |
| 9 | LP_GPIO_4 | Digital I/O | UART1 CTS |
| 10 | LP_GPIO_22 | Digital I/O | GPIO |
| 11 | LP_GPIO_23 | Digital I/O | GPIO |
| 12 | LP_GPIO_5 | Digital I/O | UART1 RTS |
| 13 | LP_GPIO_6 | Digital I/O | UART2 RXD |
| 14 | LP_GPIO_7 | Digital I/O | UART2 TXD |
| 15 | LP_GPIO_8 | Digital I/O | I2C0 SDA (high-drive pad, see Table 13-3) |
| 16 | LP_GPIO_9 | Digital I/O | I2C0 SCL (high-drive pad, see Table 13-3) |
| 17 | LP_GPIO_10 | Digital I/O | SPI0 SCK |
| 18 | LP_GPIO_11 | Digital I/O | SPI0 MOSI |
| 19 | LP_GPIO_12 | Digital I/O | SPI0 SSN |
| 20 | LP_GPIO_13 | Digital I/O | SPI0 MISO |
| 21 | VSW | PMU | DC/DC Converter Switching Node |
| 22 | VBATT_BUCK | PMU | DC/DC Converter Supply & General Battery Connection |
| 23 | VDDC_PD4 | PMU | DC/DC Converter 1.2V output and feedback node |
| 24 | GPIO_MS1 | Mixed Signal I/O | Configurable to be a GPIO Mixed Signal only (ADC interface) |
| 25 | GPIO_MS2 | Mixed Signal I/O | Configurable to be a GPIO Mixed Signal only (ADC interface) |
| 26 | CHIP_EN | PMU | Master Enable for chip |
| 27 | GPIO_MS3 | Mixed Signal I/O | Configurable to be a GPIO Mixed Signal only (ADC interface) |
| 28 | GPIO_MS4 | Mixed Signal I/O | Configurable to be a GPIO Mixed Signal only (ADC interface) |
| 29 | LP_LDO_OUT_1P2 | PMU | Low Power LDO output (connect to 1uF decoupling cap) |
| 30 | RTC_CLK_P | PMU | RTC terminal + / 32.768kHz Xtal + |
| 31 | RTC_CLK_N | PMU | RTC terminal - / 32.768kHz Xtal + |
| 32 | AO_TEST_MODE | Digital Input | Test Mode Selection (SCAN ATE) /GND for normal operation |
| 33 | AO_GPIO_0 | Digital I/O | Always On External Wakeup |
| 34 | AO_GPIO_1 | Digital I/O | Always On External Wakeup |
| 35 | AO_GPIO_2 | Digital I/O | Always On External Wakeup |
| 36 | LP_GPIO_14 | Digital I/O | UART2 CTS |

| Pin # | Pin Name | Pin Type | Description / Default Function |
|-------|------------|-------------|---|
| 37 | LP_GPIO_15 | Digital I/O | UART2 RTS |
| 38 | LP_GPIO_16 | Digital I/O | GPIO |
| 39 | VDDIO | I/O Power | I/O Supply, can be less than or equal to VBATT_BUCK |
| 40 | LP_GPIO_17 | Digital I/O | GPIO |
| 41 | LP_GPIO_18 | Digital I/O | GPIO |
| 42 | LP_GPIO_19 | Digital I/O | GPIO |
| 43 | LP_GPIO_20 | Digital I/O | GPIO |
| 44 | XO_P | Analog/RF | XO Crystal + |
| 45 | XO_N | Analog/RF | XO Crystal - |
| 46 | TPP | Analog/RF | Test Mux + output |
| 47 | TPN | Analog/RF | Test Mux – output |
| 48 | VDD_SXDIG | Analog/RF | RF Supply 1.2V |

5 Package drawing

The SAMB11 QFN package is RoHS/green compliant.

Figure 5-1. SAMB11 6x6 QFN 48 Package Outline Drawing




6 Power Management

6.1 Power Architecture

SAMB11 uses an innovative power architecture to eliminate the need for external regulators and reduce the number of off-chip components. The integrated power management block includes a DC/DC buck converter and separate Low Drop out (LDO) regulators for different power domains. The DCDC buck converter converts battery voltage to a lower internal voltage for the different circuit blocks and does this with high efficiency. The DCDC requires three external components for proper operation (two inductors L 4.7 μ H and 9.1nH, and one capacitor C 4.7 μ F).

The stacked Flash has a supply pin that is internally connected to the VDDIO pin.

Figure 6-1. SAMB11 Power Architecture



6.2 DC/DC Converter

The DC/DC Converter is intended to supply current to the BLE digital core and the RF transceiver core. The DC/DC consists of a power switch, 26MHz RC oscillator, controller, external inductor, and external capacitor. The DCDC is utilizing pulse skipping discontinuous mode as its control scheme. The DC/DC specifications are shown in the following tables and charts.

Table 6-1. DC/DC Converter Specifications (performance is guaranteed for 4.7µF L and 4.7µF C)

| Parameter | Symbol | Min. | Typ. | Max. | Unit | Note |
|---------------------------------|----------------------|-------------|------|-------------|------|--|
| Output current capability | I _{REG} | 0 | 10 | 30 | mA | Dependent on external component values and DC/DC settings with acceptable efficiency |
| External capacitor range (1) | C _{EXT} | 4.7 -10% | 4.7 | 20 | µF | External capacitance range |
| External inductor range | L _{EXT} | 2.2 -10% | 4.7 | 4.7 +10% | µH | External inductance range |
| Battery voltage | V _{BAT} | 2.35 | 3 | 4.3 | V | Functionality and stability given |
| Output voltage range | V _{REG} | 1.05 | 1.2 | 1.47 | | 25 mV step size |
| Current consumption | I _{DD} | | 125 | | µA | DC/DC quiescent current |
| Startup time | t _{startup} | 50 | | 600 | µs | Dependent on external component values and DC/DC settings |
| Voltage ripple | ΔV _{REG} | 5 | 10 | 30 | mV | Dependent on external component values and DC/DC settings |
| Efficiency | η | | 85 | | % | Measured at 3V V _{BATT} , at load of 10mA |
| Overshoot at startup | V _{OS} | | 0 | | mV | No overshoot, no output pre-charge |
| Line Regulation | ΔV _{REG} | | 10 | | | From 2.35 - 4.3V |
| Load regulation | ΔV _{REG} | | 5 | | | From 0 - 10mA |


Note External Cap: Sum of all caps connected to the DC/DC output node.

Table 6-2. DC/DC Converter Allowable Onboard Inductor and Capacitor Values (V_{BATT}=3V)

| Inductor [µH] | Efficiency [%] | V _{ripple} [mV] | | | RX Sensitivity ⁽¹⁾ [dBm] |
|---------------|----------------|--------------------------|---------|--------|-------------------------------------|
| | | C=2.2µF | C=4.7µF | C=10µF | |
| 2.2 | 83 | N/A | <5 | <5 | ~1.5dB degrade |
| 4.7 | 85 | 9 | 5 | <5 | ~0.7dB degrade |

Note: 1. Degradation relative to design powered by external LDO and DC/DC disabled.

Figure 6-2. DC/DC Converter Efficiency



6.3 Power Consumption

6.3.1 Description of Device States

SAMB11 has multiple device states, depending on the state of the ARM processor and BLE subsystem.

Note: The ARM is required to be powered on if the BLE subsystem is active.

- BLE_On_Transmit – Device is actively transmitting a BLE signal (Application may or may not be active)
- BLE_On_Receive – Device is actively receiving a BLE signal (Application may or may not be active)
- MCU_Only – Device has ARM processor powered on and BLE subsystem powered down
- Ultra_Low_Power – BLE is powered down and Application is powered down (with or without RAM retention)
- Power_Down – Device core supply off

6.3.2 Controlling the Device States

The following pins are used to switch between the main device states:

- CHIP_EN – used to enable PMU
- VDDIO – I/O supply voltage from external supply

In Power_Down state, VDDIO is on and CHIP_EN is low (at GND level). To switch between Power_Down state and MCU_Only state CHIP_EN has to change between low and high (VDDIO voltage level). Once the device is in MCU_Only state, all other state transitions are controlled entirely by software. When VDDIO is off and CHIP_EN is low, the chip is powered off with no leakage.

When no power is supplied to the device (the DC/DC Converter output and VDDIO are both off and at ground potential), a voltage cannot be applied to the SAMB11 pins because each pin contains an ESD diode from the pin to supply. This diode will turn on when voltage higher than one diode-drop is supplied to the pin.

If a voltage must be applied to the signal pads while the chip is in a low power state, the VDDIO supply must be on, so the Power_Down state must be used. Similarly, to prevent the pin-to-ground diode from turning on, do not apply a voltage that is more than one diode-drop below ground to any pin.

6.3.3 Current Consumption in Various Device States


Table 6-3. SAMB11 Device Current Consumption at VBATT=3.6V

| Device State | CHIP_EN | VDDIO | I _{VBAT} (typical) (note 3) | I _{VDDIO} (typical) (note 3) | Remark |
|--|---------|-------|---|--|--------|
| Power_Down | Off | On | <50nA | <50nA | |
| Ultra_Low_Power Standby | On | On | 900nA | 50nA | |
| Ultra_Low_Power with 8KB retention, BLE timer, no RTC ⁽¹⁾ | On | On | 1.1µA | 0.2µA | |
| Ultra_Low_Power with 8KB retention, BLE timer, with RTC ⁽²⁾ | On | On | 1.25µA | 0.1uA | |
| MCU_Only, idle (waiting for interrupt) | On | On | 0.85mA | 0.2µA | |
| BLE_On_Receive@-95dBm | On | On | 4.2mA | 0.2µA | |
| BLE_On_Transmit, 0dBm output power | On | On | 3.0mA | 0.2µA | |
| BLE_On_Transmit, 3.5dBm output power | On | On | 4.0mA | 0.2µA | |

- Notes:
1. Sleep clock derived from internal 32kHz RC oscillator.
 2. Sleep clock derived from external 32.768kHz crystal specified for CL=7pF, using the default on-chip capacitance only, without using external capacitance.
 3. Expected values for production silicon.

Note: Average advertising current for connectable beacon with full payload (37-byte packet) is targeted to be 9.7uA. The average advertising current is based on automatic advertising from the ROM with RTC 32kHz, BLE sleep timers, and 8KB memory retention. IDRAM1 and IDRAM2 are OFF. External Peripherals and debug clocks are turned OFF. VBAT is set to 3.6V. This advertising current will be enabled on a future SDK release. For current SDK based advertising current, see errata section 14.

Figure 6-3. SAMB11 Average Advertising Current



6.4 Power-Up Sequence

The power-up sequence for SAMB11 is shown in [Figure 6-4](#). The timing parameters are provided in [Table 6-4](#).

Figure 6-4. SAMB11 Power-Up Sequence




Table 6-4. SAMB11 Power-Up Sequence Timing

| Parameter | Min. | Max. | Units | Description | Notes |
|-----------|------|------|-------|--------------------------|--|
| t_{BIO} | 0 | | ms | VBATT rise to VDDIO rise | VBATT and VDDIO can rise simultaneously or can be tied together. |

| Parameter | Min. | Max. | Units | Description | Notes |
|-------------------|------|------|-------|---|---|
| t _{IOCE} | 0 | | | VDDIO rise to CHIP_EN rise | CHIP_EN must not rise before VDDIO. CHIP_EN must be driven high or low, not left floating. |
| t _{SCS} | 10 | | μs | CHIP_EN rise to 31.25kHz (2MHz/64) oscillator stabilizing | |

6.5 Power On Reset (POR) and Brown Out Detector (BOD)

The SAMB11 has a POR circuit for proper system power bring up and a brown out detector to reset the system's operation when a drop in battery voltage is detected.

- POR is a power on reset circuit that outputs a HI logic value when the VBATT_BUCK is below a voltage threshold. The POR output becomes a LO logic value when the VBATT_BUCK is above a voltage threshold.
- BOD is a brown out detector that outputs a HI logic value when the bandgap reference (BGR) voltage falls below a programmable voltage threshold. When the bandgap voltage reference voltage level is restored above a voltage threshold, the BOD output becomes a LO logic value.
- The counter creates a pulse that is HI for $256 \cdot (64 \cdot T_{2MHz}) \sim 8.2ms$

The system block diagram and timing are illustrated in [Figure 6-5](#) and [Figure 6-6](#).

Figure 6-5. SAMB11 POR and BOD Block Diagram





Figure 6-6. SAMB11 POR and BOD Timing Sequence



7 Clocking

7.1 Overview

Figure 7-1. SAMB11 Clock Architecture




Figure 7-1 provides an overview of the clock tree and clock management blocks.

The BLE Clock is used to drive the BLE subsystem. The ARM clock is used to drive the Cortex-M0 MCU and its interfaces (UART, SPI, and I²C), the nominal MCU clock speed is 26MHz. The Low Power Clock is used to drive all the low power applications like BLE sleep timer, always-on power sequencer, always-on timer, and others.

The 26MHz Crystal Oscillator (XO) must be used for the BLE operations or in the event a very accurate clock is required for the ARM subsystem operations.

The 26MHz integrated RC Oscillator is used for most general purpose operations on the MCU and its peripherals. In cases when the BLE subsystem is not used, the RC oscillator can be used for lower power consumption. The frequency variation of this RC oscillator is up to $\pm 50\%$ over process, voltage, and temperature.

The 2MHz integrated RC Oscillator can be used as the Low Power Clock for applications that require fast wakeup of the ARM or for generating a ~ 31.25 kHz clock for slower wakeup but lowest power in sleep mode. This 2MHz oscillator can also be used as the ARM Clock for low-power applications where the MCU needs to remain on but run at a reduced clock speed. The frequency variation of this RC oscillator is up to $\pm 50\%$ over process, voltage, and temperature.

The 32.768kHz RTC Crystal Oscillator (RTC XO) is recommended to be used for BLE operations (although optional) as it will reduce power consumption by providing the best timing for wakeup precision, allowing circuits to be in low power sleep mode for as long as possible until they need to wake up and connect during the BLE connection event. The ~ 31.25 kHz clock derived from the 2MHz integrated RC Oscillator can be used instead of RTC XO but it has low accuracy over process, voltage and temperature variations (up to $\pm 50\%$) and thus needs to be frequently calibrated to within ± 500 ppm if the RC oscillator is used for BLE timing during a connection event. Because this clock is less

accurate than RTC XO, it will require waking up earlier to prepare for a connection event and this will increase the average power consumption. Calibration of the RC Oscillator is described in the application note.

7.2 26MHz Crystal Oscillator (XO)

Table 7-1. SAMB11 26MHz Crystal Oscillator Parameters

| Parameter | Min | Typ | Max | Units |
|--------------------------------------|-----|-----|-----|----------|
| Crystal Resonant Frequency | N/A | 26 | N/A | MHz |
| Crystal Equivalent Series Resistance | | 50 | 150 | Ω |
| Stability - Initial Offset* | -50 | | 50 | ppm |
| Stability - Temperature and Aging | -40 | | 40 | ppm |

Note: * Initial offset must be calibrated to maintain ± 25 ppm in all operating conditions. This calibration is performed during final production testing and calibration offset values are stored in eFuse. More details are provided in the calibration application note.

The block diagram in Figure 7-2 (a) shows how the internal Crystal Oscillator (XO) is connected to the external crystal.

The XO has up to 10pF internal capacitance on each terminal XO_P and XO_N (programmable in steps of 1.25pF). To bypass the crystal oscillator, an external Signal capable of driving 10pF can be applied to the XO_P terminal as shown in Figure 7-2(b).

The needed external bypass capacitors depend on the chosen crystal characteristics. Please refer to the datasheet of the preferred crystal and take into account the on chip capacitance. When bypassing XO_P from an external clock, XO_N is required to be floating.

Figure 7-2. SAMB11 Connections to XO




Table 7-2. SAMB11 26MHz XTAL C_onchip programming

| xo_cap[3:0] | 40020808[17] | 40020848[17] | 40020814[7,6,15] | Cl,on-chip [pF] |
|-------------|--------------|--------------|------------------|-----------------|
| 0 | 0 | 0 | 000 | 1.00 |
| 1 | 0 | 0 | 001 | 2.25 |
| 2 | 0 | 0 | 010 | 3.50 |
| 3 | 0 | 0 | 011 | 4.75 |
| 4 | 0 | 0 | 100 | 6.00 |
| 5 | 0 | 0 | 101 | 7.25 |
| 6 | 0 | 0 | 110 | 8.50 |
| 7 | 0 | 0 | 111 | 9.75 |
| 8 | 1 | 1 | 000 | 6.00 |
| 9 | 1 | 1 | 001 | 7.25 |
| 10 | 1 | 1 | 010 | 8.50 |
| 11 | 1 | 1 | 011 | 9.75 |
| 12 | 1 | 1 | 100 | 11.00 |
| 13 | 1 | 1 | 101 | 12.25 |
| 14 | 1 | 1 | 110 | 13.50 |
| 15 | 1 | 1 | 111 | 14.75 |

Table 7-3 specifies the electrical and performance requirements for the external clock.

Table 7-3. SAMB11 Bypass Clock Specification

| Parameter | Min. | Max. | Unit | Comments |
|-----------------------------------|------|--------|--------|--|
| Oscillation frequency | 26 | 26 | MHz | Must be able to drive 5pF load @ desired frequency |
| Voltage swing | 0.75 | 1.2 | Vpp | |
| Stability – Temperature and Aging | -50 | +50 | ppm | BLE Spec has +-50ppm Frequency accuracy requirement. |
| Phase Noise | | -130 | dBc/Hz | At 10kHz offset |
| Jitter (RMS) | | <1psec | | Based on integrated phase noise spectrum from 1kHz to 1MHz |

7.3 32.768kHz RTC Crystal Oscillator (RTC XO)

7.3.1 General Information

SAMB11 has a 32.768kHz RTC oscillator that is preferably used for BLE activities involving connection events. To be compliant with the BLE specifications for connection events, the frequency accuracy of this clock has to be within ± 500 ppm. Because of the high accuracy of the 32.768kHz crystal oscillator clock, the power consumption can be minimized by leaving radio circuits in low-power sleep mode for as long as possible until they need to wake up for the next connection timed event.


The block diagram in [Figure 7-3\(a\)](#) shows how the internal low frequency Crystal Oscillator (XO) is connected to the external crystal.

The RTC XO has a programmable internal capacitance with a maximum of 15pF on each terminal, RTC_CLK_P and RTC_CLK_N. When bypassing the crystal oscillator with an external signal, one can program down the internal capacitance to its minimum value (~1pF) for easier driving capability. The driving signal can be applied to the RTC_CLK_P terminal as shown in [Figure 7-3\(b\)](#).

The needed external bypass capacitors depend on the chosen crystal characteristics. Please refer to the datasheet of the preferred crystal and take into account the on chip capacitance.

When bypassing RTC_CLK_P from an external clock, RTC_CLK_N is required to be floating.

Figure 7-3. SAMB11 Connections to RTC XO



(a) Crystal oscillator is used (b) Crystal oscillator is bypassed

Table 7-4. 32.768kHz XTAL C_onchip programming

| Register: pierce_cap_ctrl[3:0] | Cl_onchip (pF) |
|--------------------------------|----------------|
| 0000 | 0.0 |
| 0001 | 1.0 |
| 0010 | 2.0 |
| 0011 | 3.0 |
| 0100 | 4.0 |
| 0101 | 5.0 |
| 0110 | 6.0 |
| 0111 | 7.0 |
| 1000 | 8.0 |
| 1001 | 9.0 |
| 1010 | 10.0 |
| 1011 | 11.0 |
| 1100 | 12.0 |
| 1101 | 13.0 |
| 1110 | 14.0 |
| 1111 | 15.0 |

7.3.2 RTC XO Design and Interface Specification

The RTC consists of two main blocks: The Programmable Gm stage and tuning capacitors. The programmable Gm stage is used to maintain a phase shift of 360° with the motional arm and keep total negative resistance to sustain oscillation. Tuning capacitors are used to adjust the XO center frequency and control the XO precision for different crystal models. The output of the XO is driven to the digital domain via a digital buffer stage with supply voltage of 1.2V.

Table 7-5. RTC XO Interface

| Pin Name | Function | Register Default |
|----------------------|---|--------------------------|
| Digital Control Pins | | |
| Pierce_res_ctrl | Control feedback resistance value: 0 = 20MΩ Feedback resistance 1 = 30MΩ Feedback resistance | 0X4000F404<15>='1' |
| Pierce_cap_ctrl<3:0> | Control the internal tuning capacitors with step of 700fF: 0000=700fF 1111=11.2pF Refer to crystal datasheet to check for optimum tuning cap value | 0X4000F404<23:20>="1000" |
| Pierce_gm_ctrl<3:0> | Controls the Gm stage gain for different crystal mode: 0011= for crystal with shunt cap of 1.2pF 1000= for crystal with shunt cap >3pF | 0X4000F404<19:16>="1000" |
| Supply Pins | | |
| VDD_XO | 1.2V | |

7.3.3 RTC Characterization with Gm Code Variation at Supply 1.2V and Temp.=25°C

This section shows the RTC total drawn current and the XO accuracy versus different tuning capacitors and different GM codes, at supply voltage of 1.2V and temp.=25°C.

Figure 7-4. RTC Drawn Current vs Tuning Caps at 25°C





Figure 7-5. RTC Oscillation Frequency Deviation vs Tuning Caps at 25°C



7.3.4 RTC Characterization with Supply Variation and Temp.=25°C

Figure 7-6. RTC Drawn Current vs Supply Variation





Figure 7-7. RTC Frequency Deviation vs Supply Voltage



7.4 2MHz and 26MHz Integrated RC Oscillator

The 2MHz integrated RC Oscillator circuit without calibration has a frequency variation of 50% over process, temperature, and voltage variation. The ~31.25kHz clock is derived from the 2MHz clock by dividing by 64 and provides for lowest sleep power mode with a real-time clock running. As described above, calibration over process, temperature, and voltage is required to maintain the accuracy of this clock.

Figure 7-8. 32kHz RC Oscillator PPM Variation vs. Calibration Time at Room Temperature





Figure 7-9. 32kHz RC Oscillator Frequency Variation over Temperature



The 26MHz integrated RC Oscillator circuit has a frequency variation of 50% over process, temperature, and voltage variation.

8 CPU and Memory Subsystem

8.1 ARM Subsystem


SAMB11 has an ARM Cortex-M0 32-bit processor. It is responsible for controlling the BLE Subsystem and handling all application features.

The Cortex-M0 Microcontroller consists of a full 32-bit processor capable of addressing 4GB of memory. It has a RISC-like load/store instruction set and internal 3-stage Pipeline Von Neumann architecture.

The Cortex-M0 processor provides a single system-level interface using AMBA technology to provide high speed, low latency memory accesses.

The Cortex-M0 processor implements a complete hardware debug solution, with four hardware breakpoint and two watch point options. This provides high system visibility of the processor, memory, and peripherals through a 2-pin Serial Wire Debug (SWD) port that is ideal for microcontrollers and other small package devices.

Figure 8-1. SAMB11 ARM Cortex-M0 Subsystem



8.1.1 Features

The processor features and benefits are:

- Tight integration with the system peripherals to reduce area and development costs
- Thumb instruction set combines high code density with 32-bit performance
- Integrated sleep modes using a Wakeup Interrupt Controller for low power consumption
- Deterministic, high-performance interrupt handling via Nested Vector Interrupt Controller for time-critical applications
- Serial Wire Debug reduces the number of pins required for debugging
- DMA engine for Peripheral-to-Memory, Memory-to-Memory and Memory-to-Peripheral operation

8.1.2 Module Descriptions

8.1.2.1 Timer

The 32 bit timer block allows the CPU to generate a time tick at a programmed interval. This feature can be used for a wide variety of functions such as counting, interrupt generation, and time tracking.

8.1.2.2 Dual Timer

The APB dual-input timer module is an APB slave module consisting of two programmable 32-bit down-counters that can generate interrupts when they expire. The timer can be used in a Free-running, Periodic, or One-shot mode.

8.1.2.3 Watchdog

The two watchdog blocks allow the CPU to be interrupted if it has not interacted with the watch-dog timer before it expires. In addition, this interrupt will be an output of the core so that it can be used to reset the CPU in the event that a direct interrupt to the CPU is not useful. This will allow the CPU to get back to a known state in the event a program is no longer executing as expected. The watchdog module applies a reset to a system in the event of a software failure, providing a way to recover from software crashes.

8.1.2.4 Wake up Timer

This timer is a 32-bit count-down timer that operates on the 32kHz sleep clock. It can be used as a general purpose timer for the ARM or as a wakeup source for the chip. It has the ability to be a onetime programmable timer, as it will generate an interrupt/wakeup on expiration and stop operation. It also has the ability to be programmed in an auto reload fashion where it will generate an interrupt/wakeup and then proceed to start another count down sequence.

8.1.2.5 SPI Controller

See Section [10.3](#).

8.1.2.6 I2C Controller

See Section [10.2](#).

8.1.2.7 SPI-Flash Controller

The AHB SPI-Flash Controller is used to access an internal stacked Flash memory to access various instruction/data code needed for storing application code, code patches, and OTA images. Supports several SPI modes including 0, 1, 2, and 3.

8.1.2.8 UART

See Section [10.4](#).

8.1.2.9 DMA Controller

Direct Memory Access (DMA) allows certain hardware subsystems to access main system memory independently of the Cortex-M0 Processor.

The DMA features and benefits are:

- Supports any address alignment
- Supports any buffer size alignment
- Peripheral flow control, including peripheral block transfer
- The following modes are supported:
 - Peripheral to peripheral transfer
 - Memory to memory
 - Memory to peripheral
 - Peripheral to memory
 - Register to memory
- Interrupts for both TX done and RX done in memory and peripheral mode
- Scheduled transfers

- Endianness byte swapping
- Watchdog timer
- Four Channel operation
- 32-bit Data width
- AHB MUX (on read and write buses)
- Command lists support
- Usage of tokens

8.1.2.10 Nested Vector Interrupt Controller

External interrupt signals connect to the NVIC, and the NVIC prioritizes the interrupts. Software can set the priority of each interrupt. The NVIC and the Cortex-M0 processor core are closely coupled, providing low latency interrupt processing and efficient processing of late arriving interrupts.

All NVIC registers are accessible via word transfers and are little-endian. Any attempt to read or write a half-word or byte individually is unpredictable.

The NVIC allows the CPU to be able to individually enable, disable each interrupt source and hold each interrupt until it has been serviced and cleared by the CPU.

Table 8-1. NVIC Register Summary

| Name | Description |
|-----------|----------------------------------|
| ISER | Interrupt Set-Enable Register |
| ICER | Interrupt Clear-Enable Register |
| ISPR | Interrupt Set-Pending Register |
| ICPR | Interrupt Clear-Pending Register |
| IPR0-IPR7 | Interrupt Priority Registers |

For a description of each register, see the Cortex-M0 documentation from ARM.

8.1.2.11 GPIO Controller

The AHB GPIO is a general-purpose I/O interface unit allowing the CPU to independently control all input or output signals on SAMB11. These can be used for a wide variety of functions pertaining to the application.

The AHB GPIO provides a 16-bit I/O interface with the following features:

- Programmable interrupt generation capability.
- Programmable masking support.
- Thread safe operation by providing separate set and clear addresses for control registers.
- Inputs are sampled using a double flip-flop to avoid meta-stability issues.

8.2 Memory Subsystem

The Cortex-M0 core uses a 128kB instruction/boot ROM along with a 128kB shared instruction and data RAM.

8.2.1 Shared Instruction and Data Memory

The Instruction and Data Memory (IDRAM1 and IDRAM2) contains instructions and data used by the ARM. The size of IDRAM1 and IDRAM2 is 128kB that can be used for BLE subsystem as well as for the user application. IDRAM1 contains the three 32kB and IDRAM2 contains two 16kB memories that are accessible to the ARM and used for instruction/data storage.

8.2.2 ROM

The ROM is used to store the boot code and BLE firmware, stack and selected user profiles. ROM contains the 128kB memory that is accessible to the ARM.


8.2.3 BLE Retention Memory

The BLE functionality requires 8kB (or more depending on the application) state, instruction and data to be retained in memory when the processor either goes into Sleep Mode or Power Off Mode. The RAM is separated into specific power domains to allow tradeoff in power consumption with retention memory size.

8.3 Non-Volatile Memory

SAMB11 has 768 bits of non-volatile eFuse memory that can be read by the CPU after device reset. This non-volatile one-time-programmable memory can be used to store customer-specific parameters, such as BLE address, XO calibration information, TX power, crystal frequency offset, etc., as well as other software-specific configuration parameters. The eFuse is partitioned into six 128-bit banks. The bitmap of the first bank is shown in Figure 8-2. The purpose of the first 80 bits in bank 0 is fixed, and the remaining bits are general-purpose software dependent bits, or reserved for future use. Since each bank and each bit can be programmed independently, this allows for several updates of the device parameters following the initial programming, e.g. updating BLE address (this can be done by invalidating the last programmed bank and programming a new bank). Please refer to SAMB11 Programming Guide for the eFuse programming instructions.

Figure 8-2. SAMB11 eFuse Bit Map



8.4 Flash Memory

SAMB11 has 256kB of Flash memory, stacked on top of the MCU+BLE System on Chip. It is accessed through the SPI Flash controller and uses the 26MHz clock.

Flash memory features are:

- 256-bytes per programmable page
- Uniform 4kB Sectors, 32kB & 64kB Blocks
- Sector Erase (4K-byte)
- Block Erase (32K or 64K-byte)
- Page program up to 256 bytes <1ms
- More than 100,000 erase/write cycles and more than 20-year data retention

- 2.3V to 3.6V supply range
- 1mA active current, <1 μ A Power-down

9 Bluetooth Low Energy (BLE) Subsystem

The BLE subsystem implements all the critical real-time functions required for full compliance with Specification of the Bluetooth System, v4.1, Bluetooth SIG.

It consists of a Bluetooth 4.1 baseband controller (core), radio transceiver and the Atmel Bluetooth Smart Stack, the BLE Software Platform.

9.1 BLE Core

The baseband controller consists of modem and Medium Access Controller (MAC) and it encodes and decodes HCI packets, constructs baseband data packages, schedules frames, manages and monitors connection status, slot usage, data flow, routing, segmentation, and buffer control.

The core performs Link Control Layer management supporting the main BLE states, including advertising and connection.

9.1.1 Features

- Broadcaster, Central, Observer, Peripheral
- Simultaneous Master and Slave operation, connect up to eight slaves
- Frequency Hopping
- Advertising/Data/Control packet types
- Encryption (AES-128, SHA-256)
- Bit stream processing (CRC, whitening)
- Operating clock 52MHz

9.2 BLE Radio

The radio consists of a fully integrated transceiver, including Low Noise Amplifier, Receive (RX) down converter, and analog baseband processing as well as Phase Locked Loop (PLL), Transmit (TX) Power Amplifier, and Transmit/Receive switch. At the RF front end, no external RF components on the PCB are required other than the antenna and a matching component.

The RX sensitivity and TX output power of the radio together with the 4.1 PHY core provide a 100dB RF link budget for superior range and link reliability

9.2.1 Receiver Performance

Table 9-1. SAMB11 BLE Receiver Performance

| Parameter | Minimum | Typical | Maximum | Unit |
|---------------------------------------|---------|---------|---------|------|
| Frequency | 2,402 | | 2,480 | MHz |
| Sensitivity (maximum RX gain setting) | | -96 | | dBm |
| Sensitivity with on-chip DC/DC | | -95 | | |
| Maximum receive signal level | | +5 | | |
| CCI | | 12.5 | | dB |
| ACI (N±1) | | 0 | | |
| N+2 Blocker (Image) | | -22 | | |
| N-2 Blocker | | -38 | | |
| N+3 Blocker (Adj. Image) | | -35 | | |

| Parameter | Minimum | Typical | Maximum | Unit |
|-----------------------|---------|--------------------|---------|------|
| N-3 Blocker | | -43 | | |
| N±4 or greater | | -45 | | dB |
| Intermod (N+3, N+6) | | -32 | | dBm |
| OOB (2GHz<f<2.399GHz) | -15 | | | |
| OOB (f<2GHz) | -10 | | | |
| RX peak current draw | | 4.0 ⁽¹⁾ | | mA |

Note: 1. At -93dBm sensitivity setting. Add 0.2mA at 3.3V for best sensitivity setting.

All measurements performed at 3.6V VBATT and 25°C, with tests following Bluetooth V4.1 standard tests.

There are two gain settings for Sensitivity, high gain (-95dBm) and low gain (-93dBm). Low gain has lower current consumption.

9.2.2 Transmitter Performance

The transmitter has fine step power control with P_{out} variable in <3dB steps below 0dBm and in <0.5dB steps above 0dBm.

Table 9-2. SAMB11 BLE Transmitter Performance

| Parameter | Minimum | Typical | Maximum | Unit |
|------------------------------------|---------|--------------------|---------|------|
| Frequency | 2,402 | | 2,480 | MHz |
| Output power range | -20 | 0 | 3.5 | dBm |
| Maximum output power | | 3.5 | | |
| In-band Spurious (N±2) | | -45 | | |
| In-band Spurious (N±3) | | -50 | | |
| 2 nd harmonic P_{out} | -41 | | | |
| 3 rd harmonic P_{out} | -41 | | | |
| 4 th harmonic P_{out} | -41 | | | |
| 5 th harmonic P_{out} | -41 | | | |
| Frequency deviation | | ±250 | | kHz |
| TX peak current draw | | 3.0 ⁽¹⁾ | | mA |

Note: 1. At 0dBm TX output power.

All measurements performed at 3.6V VBATT and 25°C, with tests following Bluetooth V4.1 standard tests.

9.3 Atmel Bluetooth SmartConnect Stack

The SAMB11 has a completely integrated Bluetooth Low Energy stack on chip, fully qualified, mature and Bluetooth V4.1 compliant.

Customer applications interface with the BLE protocol stack through the Atmel BLE API, which supports direct access to the GAP, SMP, ATT, GATT client / server, and L2CAP service layer protocols in the embedded firmware.

The stack includes numerous BLE profiles for applications like:

- Smart Energy

- Consumer Wellness
- Home Automation
- Security
- Proximity Detection
- Entertainment
- Sports and Fitness
- Automotive

Together with the Atmel Studio Software Development environment, additional customer profiles can be easily developed.

The Atmel Bluetooth SmartConnect software development kit is based on Keil and IAR™ compiler tools and contains numerous application code examples for embedded and hosted modes.

In addition to the protocol stack, drivers for each peripheral hardware block are provided.

10 External Interfaces

10.1 Overview

SAMB11 external interfaces include: 2xSPI Master/Slave (SPI0 and SPI1), 2xI²C Master/Slave (I²C0 and I²C1), 2xI²C Slave-only (I²C2), 2xUART (UART1 and UART2), 1xSWD, and General Purpose Input/Output (GPIO) pins. For specific programming instructions please refer to SAMB11 Programming Guide.

Table 10-1 illustrates the different peripheral functions that are software selectable for each pin. This allows for maximum flexibility of mapping desired interfaces on GPIO pins. MUX1 option allows for any MEGAMUX option from Table 10-2 to be assigned to a GPIO.

Table 10-1. SAMB11 Pin-MUX Matrix of External Interfaces

| Pin Name | Pin # | Pull | MUX0 | MUX1 | MUX2 | MUX3 | MUX4 | MUX5 | MUX6 | MUX7 |
|------------|-------|------|---------|------------|-----------------------|-----------------------|-----------------------|-----------|------|-------------|
| LP_GPIO_0 | 5 | Up | GPIO 0 | MEGAMUX 0 | SWD CLK | | | | | TEST OUT 0 |
| LP_GPIO_1 | 6 | Up | GPIO 1 | MEGAMUX 1 | SWD IO | | | | | TEST OUT 1 |
| LP_GPIO_2 | 7 | Up | GPIO 2 | MEGAMUX 2 | UART1 RXD | | SPI1 SCK | SPI0 SCK | | TEST OUT 2 |
| LP_GPIO_3 | 8 | Up | GPIO 3 | MEGAMUX 3 | UART1 TXD | | SPI1 MOSI | SPI0 MOSI | | TEST OUT 3 |
| LP_GPIO_4 | 9 | Up | GPIO 4 | MEGAMUX 4 | UART1 CTS | | SPI1 SSN | SPI0 SSN | | TEST OUT 4 |
| LP_GPIO_5 | 12 | Up | GPIO 5 | MEGAMUX 5 | UART1 RTS | | SPI1 MISO | SPI0 MISO | | TEST OUT 5 |
| LP_GPIO_6 | 13 | Up | GPIO 6 | MEGAMUX 6 | UART2 RXD | | | SPI0 SCK | | TEST OUT 6 |
| LP_GPIO_7 | 14 | Up | GPIO 7 | MEGAMUX 7 | UART2 TXD | | | SPI0 MOSI | | TEST OUT 7 |
| LP_GPIO_8 | 15 | Up | GPIO 8 | MEGAMUX 8 | I ² C0 SDA | I ² C2 SDA | | SPI0 SSN | | TEST OUT 8 |
| LP_GPIO_9 | 16 | Up | GPIO 9 | MEGAMUX 9 | I ² C0 SCL | I ² C2 SCL | | SPI0 MISO | | TEST OUT 9 |
| LP_GPIO_10 | 17 | Up | GPIO 10 | MEGAMUX 10 | SPI0 SCK | | | | | TEST OUT 10 |
| LP_GPIO_11 | 18 | Up | GPIO 11 | MEGAMUX 11 | SPI0 MOSI | | | | | TEST OUT 11 |
| LP_GPIO_12 | 19 | Up | GPIO 12 | MEGAMUX 12 | SPI0 SSN | | | | | TEST OUT 12 |
| LP_GPIO_13 | 20 | Up | GPIO 13 | MEGAMUX 13 | SPI0 MISO | | | | | TEST OUT 13 |
| LP_GPIO_14 | 36 | Up | GPIO 14 | MEGAMUX 14 | UART2 CTS | | I ² C1 SDA | | | TEST OUT 14 |
| LP_GPIO_15 | 37 | Up | GPIO 15 | MEGAMUX 15 | UART2 RTS | | I ² C1 SCL | | | TEST OUT 15 |
| LP_GPIO_16 | 38 | Up | GPIO 16 | MEGAMUX 16 | | | SPI1 SSN | SPI0 SCK | | TEST OUT 16 |
| LP_GPIO_17 | 40 | Up | GPIO 17 | MEGAMUX 17 | | I ² C2 SDA | SPI1 SCK | SPI0 MOSI | | TEST OUT 17 |
| LP_GPIO_18 | 41 | Up | GPIO 18 | MEGAMUX 18 | | I ² C2 SCL | SPI1 MISO | SPI0 SSN | | TEST OUT 18 |
| LP_GPIO_19 | 42 | Up | GPIO 19 | MEGAMUX 19 | | | SPI1 MOSI | SPI0 MISO | | TEST OUT 19 |
| LP_GPIO_20 | 43 | Up | GPIO 20 | MEGAMUX 20 | | | | | | TEST OUT 20 |
| LP_GPIO_22 | 10 | Up | GPIO 22 | MEGAMUX 22 | | | | | | |
| LP_GPIO_23 | 11 | Up | GPIO 23 | MEGAMUX 23 | | | | | | |
| AO_GPIO_0 | 33 | Up | GPIO 31 | WAKEUP | RTC CLK IN | 32KHZ CLKOUT | | | | |
| AO_GPIO_1 | 34 | Up | GPIO 30 | WAKEUP | RTC CLK IN | 32KHZ CLKOUT | | | | |
| AO_GPIO_2 | 35 | Up | GPIO 29 | WAKEUP | RTC CLK IN | 32KHZ CLKOUT | | | | |

| Pin Name | Pin # | Pull | MUX0 | MUX1 | MUX2 | MUX3 | MUX4 | MUX5 | MUX6 | MUX7 |
|----------|-------|------|---------|------|------|------|------|------|------|------|
| GPIO_MS1 | 24 | Up | GPIO 47 | | | | | | | |
| GPIO_MS2 | 25 | Up | GPIO 46 | | | | | | | |
| GPIO_MS3 | 27 | Up | GPIO 45 | | | | | | | |
| GPIO_MS4 | 28 | Up | GPIO 44 | | | | | | | |

Table 10-2 shows the various software selectable MEGAMUX options that correspond to specific peripheral functionality. Several MEGAMUX options provides an interface to manage Wi-Fi BLE coexistence issues.

Table 10-2. SAMB11 Software Selectable MEGAMUX Options

| MUX_Sel | Function | Notes |
|---------|----------------|---|
| 0 | UART1 RXD | |
| 1 | UART1 TXD | |
| 2 | UART1 CTS | |
| 3 | UART1 RTS | |
| 4 | UART2 RXD | |
| 5 | UART2 TXD | |
| 6 | UART2 CTS | |
| 7 | UART2 RTS | |
| 8 | I2C0 SDA | |
| 9 | I2C0 SCL | |
| 10 | I2C1 SDA | |
| 11 | I2C1 SCL | |
| 12 | PWM 1 | |
| 13 | PWM 2 | |
| 14 | PWM 3 | |
| 15 | PWM 4 | |
| 16 | LP CLOCK OUT | 32kHz clock output (RC Osc or RTC XO) |
| 17 | WLAN TX ACTIVE | Coexistence: WiFi is currently transmitting |
| 18 | WLAN RX ACTIVE | Coexistence: WiFi is currently receiving |
| 19 | BLE TX ACTIVE | Coexistence: BLE is currently transmitting |
| 20 | BLE RX ACTIVE | Coexistence: BLE is currently receiving |
| 21 | BLE IN PROCESS | Coexistence Signal |
| 22 | BLE MBSY | Coexistence Signal |
| 23 | BLE SYNC | Coexistence Signal |
| 24 | BLE RXNTX | Coexistence Signal |
| 25 | BLE PTI 0 | Coexistence: BLE Priority |
| 26 | BLE PTI 1 | Coexistence: BLE Priority |

| MUX_Sel | Function | Notes |
|---------|-----------------|---------------------------|
| 27 | BLE PTI 2 | Coexistence: BLE Priority |
| 28 | BLE PTI 3 | Coexistence: BLE Priority |
| 29 | QUAD DEC X IN A | |
| 30 | QUAD DEC X IN B | |
| 31 | QUAD DEC Y IN A | |
| 32 | QUAD DEC Y IN B | |
| 33 | QUAD DEC Z IN A | |
| 34 | QUAD DEC Z IN B | |

An example of peripheral assignment using these MEGAMUX options is as follows:

- I²C0 pin-muxed on LP_GPIO_10 and LP_GPIO_11 via MUX1 and MEGAMUX=8 and 9
- I²C1 pin-muxed on LP_GPIO_0 and LP_GPIO_1 via MUX1 and MEGAMUX=10 and 11
- PWM pin-muxed on LP_GPIO_16 via MUX1 and MEGAMUX=12

Another example is to illustrate the available options for pin LP_GPIO_3, depending on the pin-MUX option selected:

- MUX0: the pin will function as bit 3 of the GPIO bus and is controlled by the GPIO controller in the ARM subsystem
- MUX1: any option from the MEGAMUX table can be selected, for example it can be a quad_dec, pwm, or any of the other functions listed in the MEGAMUX table
- MUX2: the pin will function as UART1 TXD; this can be also achieved with the MUX1 option via MEGAMUX, but the MUX2 option allows a shortcut for the recommended pinout
- MUX3: this option is not used and thus defaults to the GPIO option (same as MUX0)
- MUX4: the pin will function as SPI1 MOSI (this option is not available through MEGAMUX)
- MUX5: the pin will function as SPI0 MOSI (this option is not available through MEGAMUX)
- MUX6: the pin will function as SPI FLASH SCK (this option is not available through MEGAMUX)
- MUX7: the pin will function as bit 3 of the test output bus, giving access to various debug signals

10.2 I²C Master/Slave Interface

10.2.1 Description

The SAMB11 provides I²C Interface that can be configured as Slave or Master. The I²C Interface is a two-wire serial interface consisting of a serial data line (SDA) and a serial clock line (SCL). The SAMB11 I²C supports I²C bus Version 2.1 - 2000 and can operate in the following speed modes:

- Standard mode (100kb/s)
- Fast mode (400kb/s)
- High-speed mode (3.4Mb/s)

The I²C is a synchronous serial interface. The SDA line is a bidirectional signal and changes only while the SCL line is low, except for STOP, START, and RESTART conditions. The output drivers are open-drain to perform wire-AND functions on the bus. The maximum number of devices on the bus is limited by only the maximum capacitance specification of 400pF. Data is transmitted in byte packages.

For specific information, refer to the Philips Specification entitled "The I²C -Bus Specification, Ver2.1".

10.2.2 I²C Interface Timing

The I²C Interface timing (common to Slave and Master) is provided in Figure 10-1. The timing parameters for Slave and Master modes are specified in Table 10-3 and Table 10-4 respectively.

Figure 10-1. SAMB11 I²C Slave Timing Diagram




Table 10-3. SAMB11 I²C Slave Timing Parameters

| Parameter | Symbol | Min. | Max. | Units | Remarks |
|--------------------------------------|-------------|---------|------|---------|---|
| SCL Clock Frequency | f_{SCL} | 0 | 400 | kHz | |
| SCL Low Pulse Width | t_{WL} | 1.3 | | μ s | |
| SCL High Pulse Width | t_{WH} | 0.6 | | | |
| SCL, SDA Fall Time | t_{HL} | | 300 | ns | This is dictated by external components |
| SCL, SDA Rise Time | t_{LH} | | 300 | | |
| START Setup Time | t_{SUSTA} | 0.6 | | μ s | |
| START Hold Time | t_{HDSTA} | 0.6 | | | |
| SDA Setup Time | t_{SUDAT} | 100 | | ns | Slave and Master Default Master Programming Option |
| SDA Hold Time | t_{HDDAT} | 0 40 | | | |
| STOP Setup time | t_{SUSTO} | 0.6 | | μ s | |
| Bus Free Time Between STOP and START | t_{BUF} | 1.3 | | | |
| Glitch Pulse Reject | t_{PR} | 0 | 50 | ns | |

Table 10-4. SAMB11 I²C Master Timing Parameters

| Parameter | Symbol | Standard Mode | | Fast Mode | | High-speed Mode | | Units |
|----------------------|-------------|---------------|------|-----------|------|-----------------|------|---------|
| | | Min. | Max. | Min. | Max. | Min. | Max. | |
| SCL Clock Frequency | f_{SCL} | 0 | 100 | 0 | 400 | 0 | 3400 | kHz |
| SCL Low Pulse Width | t_{WL} | 4.7 | | 1.3 | | 0.16 | | μ s |
| SCL High Pulse Width | t_{WH} | 4 | | 0.6 | | 0.06 | | |
| SCL Fall Time | t_{HLSC} | | 300 | | 300 | 10 | 40 | ns |
| SDA Fall Time | t_{HLSDA} | | 300 | | 300 | 10 | 80 | |

| Parameter | Symbol | Standard Mode | | Fast Mode | | High-speed Mode | | Units |
|--------------------------------------|---------------------|---------------|------|-----------|-----|-----------------|----|-------|
| SCL Rise Time | t _{LH} SCL | | 1000 | | 300 | 10 | 40 | |
| SDA Rise Time | t _{LH} SDA | | 1000 | | 300 | 10 | 80 | |
| START Setup Time | t _{SUSTA} | 4.7 | | 0.6 | | 0.16 | | μs |
| START Hold Time | t _{HDSTA} | 4 | | 0.6 | | 0.16 | | |
| SDA Setup Time | t _{SUDAT} | 250 | | 100 | | 10 | | ns |
| SDA Hold Time | t _{HDDAT} | 5 | | 40 | | 0 | 70 | |
| STOP Setup time | t _{SUSTO} | 4 | | 0.6 | | 0.16 | | μs |
| Bus Free Time Between STOP and START | t _{BUF} | 4.7 | | 1.3 | | | | |
| Glitch Pulse Reject | t _{PR} | | | 0 | 50 | | | ns |

10.3 SPI Master/Slave Interface

10.3.1 Description

SAMB11 provides a Serial Peripheral Interface (SPI) that can be configured as Master or Slave. The SPI Interface pins are mapped as shown in [Table 10-5](#). The SPI Interface is a full-duplex slave-synchronous serial interface. When the SPI is not selected, i.e., when SSN is high, the SPI interface will not interfere with data transfers between the serial-master and other serial-slave devices. When the serial slave is not selected, its transmitted data output is buffered, resulting in a high impedance drive onto the serial master receive line. The SPI Slave interface responds to a protocol that allows an external host to read or write any register in the chip as well as initiate DMA transfers. For the details of the SPI protocol and more specific instructions, refer to SAMB11 Programming Guide.

Table 10-5. SAMB11 SPI Interface Pin Mapping

| Pin Name | SPI Function |
|----------|----------------------------|
| SSN | Active Low Slave Select |
| SCK | Serial Clock |
| MOSI | Master Out Slave In (Data) |
| MISO | Master In Slave Out (Data) |


10.3.2 SPI Interface Modes

The SPI Interface supports four standard modes as determined by the Clock Polarity (CPOL) and Clock Phase (CPHA) settings. These modes are illustrated in Table 10-6 and Figure 10-2. The red lines in Figure 10-2 correspond to Clock Phase = 0 and the blue lines correspond to Clock Phase = 1.

Table 10-6. SAMB11 SPI Modes

| Mode | CPOL | CPHA |
|------|------|------|
| 0 | 0 | 0 |
| 1 | 0 | 1 |
| 2 | 1 | 0 |
| 3 | 1 | 1 |

Figure 10-2. SAMB11 SPI Clock Polarity and Clock Phase Timing



10.3.3 SPI Slave Timing

The SPI Slave timing is provided in [Figure 10-3](#) and [Table 10-7](#).

Figure 10-3. SAMB11 SPI Slave Timing Diagram




Table 10-7. SAMB11 SPI Slave Timing Parameters

| Parameter | Symbol | Min. | Max. | Units |
|-------------------------|-------------|------|------|-------|
| Clock Input Frequency | f_{SCK} | | 2 | MHz |
| Clock Low Pulse Width | t_{WL} | 240 | | ns |
| Clock High Pulse Width | t_{WH} | 240 | | |
| Clock Rise Time | t_{LH} | | 10 | |
| Clock Fall Time | t_{HL} | | 10 | |
| Input Setup Time | t_{ISU} | 5 | | |
| Input Hold Time | t_{IHD} | 5 | | |
| Output Delay | t_{ODLY} | 0 | 20 | |
| Slave Select Setup Time | t_{SUSSN} | 5 | | |
| Slave Select Hold Time | t_{HDSSN} | 5 | | |

10.3.4 SPI Master Timing

The SPI Master Timing is provided in [Figure 10-4](#) and [Table 10-8](#).

Figure 10-4. SAMB11 SPI Master Timing Diagram




Table 10-8. SAMB11 SPI Master Timing Parameters

| Parameter | Symbol | Min. | Max. | Units |
|------------------------|------------|------|------|-------|
| Clock Output Frequency | f_{SCK} | | 4 | MHz |
| Clock Low Pulse Width | t_{WL} | 120 | | ns |
| Clock High Pulse Width | t_{WH} | 120 | | |
| Clock Rise Time | t_{LH} | | 5 | |
| Clock Fall Time | t_{HL} | | 5 | |
| Input Setup Time | t_{ISU} | 5 | | |
| Input Hold Time | t_{IHD} | 5 | | |
| Output Delay | t_{ODLY} | 0 | 5 | |

10.4 UART Interface

SAMB11 provides Universal Asynchronous Receiver/Transmitter (UART) interfaces for serial communication. The Bluetooth subsystem has two UART interfaces: a 4-pin interface for control and data transfer. The UART interfaces are compatible with the RS-232 standard, where SAMB11 operates as Data Terminal Equipment (DTE). The 2-pin UART has the receive and transmit pins (RXD and TXD), and the 4-pin UART has two additional pins used for flow control/handshaking: Request To Send (RTS) and Clear To Send (CTS). **The RTS and CTS are used for hardware flow control; they MUST be connected to the host MCU UART and enabled for the UART interface to be functional.** The pins associated with each UART interfaces can be enabled on several alternative pins by programming their corresponding pin-MUX control registers (see [Table 10-1](#) and [Table 10-2](#) for available options).

The UART features programmable baud rate generation with fractional clock division, which allows transmission and reception at a wide variety of standard and non-standard baud rates. The Bluetooth UART input clock is selectable between 26MHz, 13MHz, 6.5MHz, and 3.25MHz. The clock divider value is programmable as 13 integer bits and three fractional bits (with 8.0 being the smallest recommended value for normal operation). This results in the maximum supported baud rate of $26\text{MHz}/8.0 = 3.25\text{MBd}$.


The UART can be configured for seven or eight bit operation, with or without parity, with four different parity types (odd, even, mark, or space), and with one or two stop bits. It also has RX and TX FIFOs, which ensure reliable high speed reception and low software overhead transmission. FIFO size is 4 x 8 for both RX and TX direction. The UART

also has status registers showing the number of received characters available in the FIFO and various error conditions, as well the ability to generate interrupts based on these status bits.

An example of UART receiving or transmitting a single packet is shown in [Figure 10-5](#). This example shows 7-bit data (0x45), odd parity, and two stop bits.

For more specific instructions please refer to SAMB11 Programming Guide.

Figure 10-5. Example of UART Rx or Tx packet



10.5 GPIOs

30 General Purpose Input/Output (GPIO) pins total, labeled LP_GPIO, GPIO_MS, and AO_GPIO, are available to allow for application specific functions. Each GPIO pin can be programmed as an input (the value of the pin can be read by the host or internal processor) or as an output. The host or internal processor can program output values.

LP_GPIO are digital interface pins, GPIO_MS are mixed signal/analog interface pins and AO_GPIO is an always-on digital interface pin that can detect interrupt signals while in deep sleep mode for wake-up purposes.


The LP_GPIO have interrupt capability, but only when in active/standby mode. In sleep mode, they are turned off to save power consumption.

10.6 Analog to Digital Converter (ADC)

10.6.1 Overview

The SAMB11 has an integrated Successive Approximation (SAR) ADC with 11-bit resolution and variable conversion speed up 1MS/s. The key building blocks are the capacitive DAC, comparator, and synchronous SAR engine as shown in [Figure 10-6](#).

Figure 10-6. SAMB11 SAR ADC Block Diagram



The ADC reference voltage can be either generated internally or set externally via one of the four available Mixed Signal GPIO pins on the SAMB11.

There are two modes of operation:

- A. High resolution (11-bit): Set the reference voltage to half the supply voltage or below. In this condition the input signal dynamic range is equal to twice the reference voltage (ENOB=10bit).
- B. Medium Resolution (10-bit) : Set the reference voltage to any value below supply voltage (up to supply voltage - 300mV) and in this condition the input dynamic range is from zero to reference voltage (ENOB = 9bit).

There are four input channels that are time multiplexed to the input of the SAR ADC.

In power saving mode, the internal reference voltage is completely off and the reference voltage is set externally.

The ADC characteristics are summarized in [Table 10-9](#).

Table 10-9. SAR ADC Characteristics

| Conversion rate | 1ks → 1MS |
|-----------------------|------------------------------------|
| Selectable Resolution | 10 → 11bit |
| Power consumption | 13.5µA (at 100KS/s) ⁽¹⁾ |

Note: 1. With external reference.

10.6.2 Timing

The ADC timing is shown in [Figure 10-7](#). The input signal is sampled twice, in the first sampling cycle the input range is defined either to be above reference voltage or below it and in the second sampling instant the ADC start its normal operation.

The ADC takes two sampling instants and N-1 conversion cycle (N=ADC resolution) and one cycle to sample the data out. Therefore, for 11-bit resolution it takes 13 clock cycles to do one Sample conversion.


The Input clock equals N+2 the sampling clock frequency (N is the ADC resolution).

CONV signal : Gives indication about end of conversion.

SAMPL :The input signal is sampled when this signal is high.

RST ENG :When High SAR Engine is in reset mode (SAR engine output is set to mid-scale).

Figure 10-7. SAR ADC Timing



10.6.3 Performance

Table 10-10. Static Performance of SAR ADC

| Parameter | Condition | Min | Typ | Max | Unit |
|---------------------|-----------|-----|-----|------|------|
| Input voltage range | | 0 | | VBAT | V |

| Parameter | Condition | Min | Typ | Max | Unit |
|-----------------------------|---|-------|----------------------|-------|--------------|
| Resolution | | | 11 | | bits |
| Sample rate | | | 100 | 1000 | KSPS |
| Input offset | Internal VREF | -10 | | +10 | mV |
| Gain error | Internal VREF | -4 | | +4 | % |
| DNL | 100KSPS. Internal VREF=1.6V. Same result for external VREF. | -0.75 | | +1.75 | LSB |
| INL | 100KSPS. Internal VREF=1.6V. Same result for external VREF. | -2 | | +2.5 | |
| THD | 1.1.1.1 1kHz sine input at 100KSPS | | 73 | | dB |
| SINAD | 1kHz sine input at 100KSPS | | 62.5 | | |
| SFDR | 1kHz sine input at 100KSPS | | 73.7 | | |
| Conversion time | | | 13 | | cycles |
| Current consumption | Using external VREF, at 100KSPS. | | 13.5 | | μ A |
| | Using internal VREF, at 100KSPS. | | 25.0 | | |
| | Using external VREF, at 1MSPS | | 94 | | |
| | Using internal VREF, at 1MSPS | | 150 | | |
| | Using internal VREF, during VBAT monitoring | | 100 | | |
| | Using internal VREF, during temperature monitoring | | 50 | | |
| Internal reference voltage | Mean value using VBAT=2.5V | | 1.026 ⁽¹⁾ | | V |
| | Standard deviation across parts | | 10.5 | | |
| VBAT Sensor Accuracy | Without calibration | -55 | | +55 | mV |
| | With offset & gain calibration | -17 | | +17 | |
| Temperature Sensor Accuracy | Without calibration | -9 | | +9 | $^{\circ}$ C |
| | With offset calibration | -4 | | +4 | |

Note: 1. Effective VREF is 2xInternal Reference Voltage

$T_C = 25^{\circ}C$ $V_{BAT} = 3.0V$, unless otherwise noted

Figure 10-8. INL of SAR ADC




Figure 10-9. DNL of SAR ADC






Figure 10-10. Sensor ADC Dynamic Measurement with Sinusoidal Input



- Notes:
1. 25°C, 3.6V VBAT, and 100kS/s
Input Signal: 1kHz sine wave, 3Vp-p amplitude
 2. SNDR = 62.6dB
SFDR = 73.7dB
THD=73.0db

Figure 10-11. Sensor ADC dynamic performance summary at 100KSPS



10.7 Software Programmable Timer and Pulse Width Modulator

SAMB11 contains four individually configurable pulse width modulator (PWM) blocks to provide external control voltages. The base frequency of the PWM block (f_{PWM_base}) is derived from the XO clock (26MHz) or the RC oscillator followed by a programmable divider.

The frequency of each PWM pulse (f_{PWM}) is programmable in steps according to the following relationship:

$$f_{PWM} = \frac{f_{PWM_base}}{64 * 2^i} \quad i = 0,1,2, \dots, 8$$

The duty cycle of each PWM signal is configurable with 10-bit resolution (minimum duty cycle is 1/1024 and maximum is 1023/1024).

f_{PWM_base} can be selected to have different values according to the following table. Minimum and maximum frequencies supported for each clock selection are listed in the table as well.

Table 10-11. f_{PWM} Range for Different f_{PWM} Base Frequencies

| f_{PWM_base} | f_{PWM} max | f_{PWM} min |
|-----------------|---------------|---------------|
| 26MHz | 406.25kHz | 6.347kHz |
| 13MHz | 203.125kHz | 3.173kHz |
| 6.5MHz | 101.562kHz | 1.586kHz |
| 3.25MHz | 50.781kHz | 793.25Hz |

10.8 Clock Output

SAMB11 has an ability to output a clock. The clock can be output to any GPIO pin via the test MUX. Note that this feature requires that the ARM and BLE power domains stay on. If BLE is not used, the clocks to the BLE core are gated off, resulting in small leakage. The following two methods can be used to output a clock.

10.8.1 Variable Frequency Clock Output Using Fractional Divider

SAMB11 can output the variable frequency ADC clock using a fractional divider of the 26MHz oscillator. This clock needs to be enabled using bit 10 of the `lpmcu_clock_enables_1` register. The clock frequency can be controlled by the divider ratio using the `sens_adc_clk_ctrl` register (12-bits integer part, 8-bit fractional part). The division ratio can vary from 2 to 4096 delivering output frequency between 6.35kHz to 13MHz. This is a digital divider with pulse swallowing implementation so the clock edges may not be at exact intervals for the fractional ratios. However, it is exact for integer division ratios.

10.8.2 Fixed Frequency Clock Output

SAMB11 can output the following fixed-frequency clocks:

- 52MHz derived from XO
- 26MHz derived from XO
- 2MHz derived from the 2MHz RC Osc.
- 31.25kHz derived from the 2MHz RC Osc.
- 32.768kHz derived from the RTC XO
- 26MHz derived from 26MHz RC Osc.
- 6.5MHz derived from XO
- 3.25MHz derived from 26MHz RC Osc.

For clocks 26MHz and above ensure that external pad load on the board is minimized to get a clean waveform.

10.9 Three-Axis Quadrature Decoder

SAMB11 has a three-axis Quadrature decoder (X, Y, and Z) that can determine the direction and speed of movement on three axes, requiring in total six GPIO pins to interface with the sensors. The sensors are expected to provide pulse trains as inputs to the quadrature decoder.

Each axis channel input will have two pulses with ± 90 degrees phase shift depending on the direction of movement. The decoder counts the edges of the two waveforms to determine the speed and uses the phase relationship between the two inputs to determine the direction of motion.

The decoder is configured to interrupt ARM based on independent thresholds for each direction. Each quadrature clock counter (X, Y, and Z) is an unsigned 16-bit counter and the system clock uses a programmable sampling clock ranging from 26MHz, 13, 6.5, to 3.25MHz.

If wakeup is desired from threshold detection on an axis input, the always-on GPIO needs to be used.

12 Bill of Material (BOM)

Figure 12-1. SAMB11 QFN SoC BOM

| Item | Qty | Reference | Value | Description | Manufacturer | Part Number | Manufacturer 2 | Part Number2 | Footprint |
|------|-----|----------------|---------------|--|--------------|-----------------------|----------------|-------------------|-----------------|
| 1 | 1 | ANTENNA | | Antenna, ceramic, 2.4-2.5GHz, 50ohm, -40 -+85C | | | | | |
| 2 | 1 | C1 | 10uF | CAP,CER,10uF,20%,X5R,0402,4V,-55-85C | TDK | CL00A5X5R0G106M | Taiyo Yuden | AVIK105CBJ106MV F | 0402 |
| 3 | 1 | C4 | 1.8pF | CAP,CER,1.8pF,+/-0.1pF,NPO,0201,25V,-55-125C | TDK | C0603COG1E1R8C | | | 0201 |
| 4 | 1 | C5 | DNI | CAP,CER,1.0pF,+/-0.1pF,NPO,0201,25V,-55-125C | Murata | GRM0335C1E1R0BA01J | | | 0201 |
| 5 | 1 | C6 | 3.9pF | CAP,CER,3.9pF,+/-0.1pF,NPO,0201,25V,-55-125C | Samsung | CL03C3R9BA3GNIC | | | 0201 |
| 6 | 2 | C7,C8 | 5.6pF | CAP,CER,5.6pF,+/-0.5pF,NPO,0201,25V,-55-125C | TDK | C0603COG1E1F5R6G030BA | | | 0201 |
| 7 | 4 | C9,C10,C11,C15 | 0.1uF | CAP,CER,0.1uF,10%,X5R,0201,6.3V,-55-125C | Murata | GRM033R60J04KE19D | | | 0201 |
| 8 | 1 | C12 | 2.2uF | CAP,CER,2.2uF,10%,X5R,0402,6.3V,-55-85C | TDK | CL00A5X5R0J225K | | | 0402 |
| 9 | 1 | C13 | 1.0uF | CAP,CER,1.0uF,20%,X5R,0201,4V,-55-85C | TDK | C0603X5R0105M0308C | Samsung | CL03A105KQ3C5NC | 0201 |
| 10 | 1 | C14 | 4.7uF | CAP,CER,4.7uF,10%,X5R,0402,6.3V,-55-85C | TDK | CL00A5X5R01475K0508C | | | 0402 |
| 11 | 1 | C17 | 1.0uF | CAP,CER,1.0uF,20%,X55,0201,4V,-55-85C | Murata | GRM033C80G105MEA2D | | | 0201 |
| 12 | 1 | C20 | 0.01uF | CAP,CER,0.01uF,10%,X5R,0201,10V,-55-125C | Murata | GRM033R61A103KA01D | | | 0201 |
| 13 | 2 | FB1,FB2 | BLM03AG1215N1 | INDUCTOR,Multilayer,9.1nH,5%,300mA,0.32 ohms@8@100MHz,-55-125C | Murata | BLM03AG1215N1 | | | 0201 |
| 14 | 1 | L4 | 3nH | FERRITE,120 OHM @100MHz,200mA,0201,-55-125C | Taiyo Yuden | HKO0603S3N0C-T | | | 0201 |
| 15 | 1 | L5 | 9.1nH | INDUCTOR,Multilayer,9.1nH,5%,300mA,0.32 ohms@8@100MHz,-55-125C,0402 | Murata | LOG15HS9N1J02D | | | 0402 |
| 16 | 1 | L6 | 4.7uH | INDUCTOR,unshielded,4.7uH,20%,120mA Saturation,0.5ohms,SRF=80MHz,0603,-55-125C | TDK | MLZ1608V4R7W7000 | | | 0603 |
| 17 | 2 | R1,R4 | DNI | RESISTOR,Thick Film,0 ohm,0201 | Panasonic | ERJ-1GN0R00C | | | 0201 |
| 18 | 2 | R2,R3 | DNI | RESISTOR,Thick Film,0 ohm,0201 | Panasonic | ERJ-1GN0R00C | | | 0201 |
| 19 | 2 | TP1,TP2 | Non-component | Test Point,Surface Mount,0.040"sq w/0.25"hole | | | | | 0.04"SQx0.025"H |
| 20 | 1 | U1 | SAMB11 | IC, BLE, Stacked FLASH, 48QFN | Atmel | SAMB11 | | | 48QFN |
| 21 | 1 | V1 | 26MHz | CRYSTAL,26MHz,CL=8pF, 20ppm temp.,-40-85C,ESR=80,2.5x2mm | Taitien | A0183-X-001-3 | | | 2.5x2.0mm |
| 22 | 1 | V2 | 32.768KHz | Crystal, 32.768KHz,+/-20ppm,-40-+85C,CL=7pF, 2 lead, 5V | ECS | ECS-327-7-39-TR | | | |

SAMB11 Reference Schematic Revised: Thursday, January 21, 2016
 SAMB11 Ref Revision: 5

Bill Of Materials February 2, 2016 17:11:44

13 Electrical Characteristics

13.1 Absolute Maximum Ratings

Table 13-1. SAMB11 Absolute Maximum Ratings

| Symbol | Characteristic | Min | Max | Unit |
|------------------------------------|------------------------|-------------------------------|-------------------------------|------|
| VDDIO | I/O Supply Voltage | -0.3 | 5.0 | V |
| VBATT | Battery Supply Voltage | -0.3 | 5.0 | |
| V _{IN} ⁽¹⁾ | Digital Input Voltage | -0.3 | VDDIO | |
| V _{AIN} ⁽²⁾ | Analog Input Voltage | -0.3 | 1.5 | |
| V _{ESDHBM} ⁽³⁾ | ESD Human Body Model | -1000, -2000(see notes below) | +1000, +2000(see notes below) | |
| T _A | Storage Temperature | -65 | 150 | °C |
| | Junction Temperature | | 125 | |

- Note:
- V_{IN} corresponds to all the digital pins
 - V_{AIN} corresponds to all the analog pins
 - For V_{ESDHBM}, each pin is classified as Class 1, or Class 2, or both:
 - The Class 1 pins include all the pins (both analog and digital)
 - The Class 2 pins include all digital pins only
 - V_{ESDHBM} is ±1kV for Class1 pins. V_{ESDHBM} is ±2kV for Class2 pins

13.2 Recommended Operating Conditions

Table 13-2. SAMB11 Recommended Operating Conditions

| Symbol | Characteristic | Min | Typ | Max | Units |
|--------|---------------------------------------|-----|-----|-----|-------|
| VDDIO | I/O Supply Voltage ⁽¹⁾ | 2.3 | 3 | 4.3 | V |
| VBATT | Battery Supply Voltage ⁽¹⁾ | 2.3 | 3 | 4.3 | |
| | Operating Temperature | -40 | | 85 | °C |

- Note:
- VBATT must not be less than VDDIO

13.3 DC Characteristics

Table 13-3 provides the DC characteristics for the SAMB11 digital pads.

Table 13-3. SAMB11 DC Electrical Characteristics

| VDDIO Condition | Characteristic | Min. | Typ. | Max. | Unit |
|-----------------|---|------------|------|----------------------------|------|
| VDDIOM | Input Low Voltage VIL | -0.30 | | 0.63 | V |
| | Input High Voltage VIH | VDDIO-0.60 | | VDDIO+0.30 | |
| | Output Low Voltage VOL | | | 0.45 | |
| | Output High Voltage VOH | VDDIO-0.50 | | | |
| VDDIOH | Input Low Voltage VIL | -0.30 | | 0.65 | |
| | Input High Voltage VIH | VDDIO-0.60 | | VDDIO+0.30 (up to 3.60) | |
| | Output Low Voltage VOL | | | 0.45 | |
| | Output High Voltage VOH | VDDIO-0.50 | | | |
| All | Output Loading | | | 20 | pF |
| | Digital Input Load | | | 6 | |
| VDDIOM | Pad drive strength (regular pads) ⁽¹⁾ | 3.4 | 6.6 | | mA |
| VDDIOH | Pad drive strength (regular pads) ⁽¹⁾ | 10.5 | 14 | | |
| VDDIOM | Pad drive strength (high-drive pads) ⁽¹⁾ | 6.8 | 13.2 | | |
| VDDIOH | Pad drive strength (high-drive pads) ⁽¹⁾ | 21 | 28 | | |

Note: 1. The following are high-drive pads: GPIO_8, GPIO_9; all other pads are regular.

14 Errata

Issue: In the ATSAMB11 Datasheet, the measured advertisement current for the cases listed in Table 6-3 will be higher than what is reported.

SDK5.0 does not resemble the same conditions where Table 6-3 has been measured.

For example:

The power and timing parameters in the SDK5.0 release have not been fully optimized to their final values.

IDRAM1 and IDRAM2 are always enabled/retained for ROM patches and application development.

SDK5.0 enables clocks to different peripheral blocks to allow easier application development.

Continuous access to the SWD debug interface is needed. Therefore, debug clocks cannot be turned OFF.

A small sample measurement has been performed they show the following results:

Measurement condition:

- 1-sec adverting interval.
- 37 byte advertising payload.
- Connectable beacon
- Advertising on 3 channels (37,38,39).
- VBAT and VDDIO are set to 3.3V.

Average advertising current: 13.65 μ A

Average sleep current between beacons: 2.00 μ A

With VBAT set to 3.6V, the average advertising current under the same conditions is 12.67 μ A.

15 Document Revision History

| Doc Rev. | Date | Comments |
|----------|---------|---|
| 42426C | 02/2016 | <ol style="list-style-type: none"> 1. Updated current numbers in the feature list 2. Updated DC/DC Converter data ion section 6.2 and Table 6-1 and provided efficiency graph in Figure 6-2 3. Updated current numbers and added comments in Table 6-3 4. Updated advertising current chart in Figure 6-3 5. Revised Notes in Section 6.5, updated Figure 6-5 and Figure 6-6 6. New figure for Clock Architecture in Figure 7-1 7. Revised values in Table 7-1 8. Added new figures in Figure 7-2 and Figure 7-3 9. Updated capacitance value in section 7.2 10. Updated voltage value in Table 7-3 11. Added table for 26MHz onchip programming in Table 7-4 12. Updated capacitance value and text in section 7.3.1 13. Added 32kHz RC Oscillator performance charts in Section 7.3 14. Revised and added more detailed data to Section 8.1 15. Updated eFuse and Flash information Sections 8.3, 8.4 and Figure 8-2 16. Updated Receiver performance numbers and comments in Table 9-1 17. Updated Transmitter performance numbers and comments in Table 9-2 18. Added notice about UART Flow Control in Section 10.4 19. Replaced the whole ADC performance Table 10-10 20. Revised values in SPI Slave timing in Table 10-7 21. Revised values om SPI Master timing in Table 10-8 22. Updated ADC power consumption and added comment in Table 10-9 23. Replaced ADC performance charts: Figure 10-8 and Figure 10-9 24. Added new ADC performance charts: Figure 10-10 and Figure 10-11 25. Added f_{pwm} range table in Table 10-11 for the software Programmable times. 26. Revised reference schematics in Section 11 27. Revised Table 13-1 showing more Pad drive strength. 28. Added section 14 Errata |

| Doc Rev. | Date | Comments |
|----------|---------|---|
| 42426B | 07/2015 | <ol style="list-style-type: none"> 1. Updated feature list (peripherals, clock, and power bullets) 2. Updated pinout information in Section 4 3. Updated power architecture drawing in (Figure 6-1) 4. Added DC/DC converter description (Section 6.2) 5. Updated power consumption numbers and description (Section 6.3) 6. Minor correction in power-up sequence (Section 6.4) 7. Minor correction in POR and BOD description (Section 6.5) 8. Updated clocking description, figures, charts, and numbers (Section 0) 9. Updated eFuse map (Figure 8-2) 10. Updated receiver and transmitter performance numbers (Table 9-1 and Table 9-2) 11. Updated pin MUX description and tables (Section 10.1) 12. Merged I2C master and slave into one section (Section 10.2) 13. Added SPI master (Section 10.3), updated description and fixed typos in timing 14. Removed SPI Flash from the document 15. Updated ADC performance numbers and added figures (Section 10.6) 16. Updated PWM numbers and added table (Section 10.7) 17. Added Clock Output section (Section 10.8) 18. Updated max VBATT and VDDIO voltage and added a note on VBATT (Section 13.2) 19. Added pad drive strength numbers (Table 13-3) 20. Miscellaneous minor updates, corrections, and formatting changes throughout the document |
| 42426A | 03/2015 | Initial document release |



Atmel®, Atmel logo and combinations thereof, Enabling Unlimited Possibilities®, and others are registered trademarks or trademarks of Atmel Corporation in U.S. and other countries. ARM® and Cortex® are the registered trademarks or trademarks of ARM Ltd. Other terms and product names may be trademarks of others.

DISCLAIMER: The information in this document is provided in connection with Atmel products. No license, express or implied, by estoppel or otherwise, to any intellectual property right is granted by this document or in connection with the sale of Atmel products. EXCEPT AS SET FORTH IN THE ATMEL TERMS AND CONDITIONS OF SALES LOCATED ON THE ATMEL WEBSITE, ATMEL ASSUMES NO LIABILITY WHATSOEVER AND DISCLAIMS ANY EXPRESS, IMPLIED OR STATUTORY WARRANTY RELATING TO ITS PRODUCTS INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT. IN NO EVENT SHALL ATMEL BE LIABLE FOR ANY DIRECT, INDIRECT, CONSEQUENTIAL, PUNITIVE, SPECIAL OR INCIDENTAL DAMAGES (INCLUDING, WITHOUT LIMITATION, DAMAGES FOR LOSS AND PROFITS, BUSINESS INTERRUPTION, OR LOSS OF INFORMATION) ARISING OUT OF THE USE OR INABILITY TO USE THIS DOCUMENT, EVEN IF ATMEL HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. Atmel makes no representations or warranties with respect to the accuracy or completeness of the contents of this document and reserves the right to make changes to specifications and products descriptions at any time without notice. Atmel does not make any commitment to update the information contained herein. Unless specifically provided otherwise, Atmel products are not suitable for, and shall not be used in, automotive applications. Atmel products are not intended, authorized, or warranted for use as components in applications intended to support or sustain life.

SAFETY-CRITICAL, MILITARY, AND AUTOMOTIVE APPLICATIONS DISCLAIMER: Atmel products are not designed for and will not be used in connection with any applications where the failure of such products would reasonably be expected to result in significant personal injury or death ("Safety-Critical Applications") without an Atmel officer's specific written consent. Safety-Critical Applications include, without limitation, life support devices and systems, equipment or systems for the operation of nuclear facilities and weapons systems. Atmel products are not designed nor intended for use in military or aerospace applications or environments unless specifically designated by Atmel as military-grade. Atmel products are not designed nor intended for use in automotive applications unless specifically designated by Atmel as automotive-grade.