

# LMV321/LMV358/LMV358-Q1/LMV358-Q3/LMV324 Single/Dual/Quad General Purpose, Low Voltage, Rail-to-Rail Output Operational Amplifiers

 Check for Samples: [LMV321-N](#), [LMV358-N](#), [LMV358-N-Q1](#), [LMV358-N-Q3](#), [LMV324-N](#)

## FEATURES

- (For  $V^+ = 5V$  and  $V^- = 0V$ , unless otherwise specified)
- LMV358 is available in Automotive AEC-Q100 Grade 1 version
- Guaranteed 2.7V and 5V performance
- No crossover distortion
- Industrial temperature range  $-40^{\circ}C$  to  $+125^{\circ}C$
- Gain-bandwidth product 1 MHz
- Low supply current
- LMV321 130  $\mu A$
- LMV358 210  $\mu A$
- LMV324 410  $\mu A$
- Rail-to-rail output swing @ 10 k $\Omega$   $V^+ - 10$  mV &  $V^- + 65$  mV
- $V_{CM}$  Range  $-0.2V$  to  $V^+ - 0.8V$

## APPLICATIONS



- Active filters
- General purpose low voltage applications
- General purpose portable devices

## DESCRIPTION

The LMV358/LMV324 are low voltage (2.7V to 5.5V) versions of the dual and quad commodity op amps LM358/LM324 (5V to 30V). The LMV321 is the single channel version. The LMV321/LMV358/LMV324 are the most cost effective solutions for applications where low voltage operation, space efficiency, and low price are important. They offer specifications that meet or exceed the familiar LM358/LM324. The LMV321/LMV358/LMV324 have rail-to-rail output swing capability and the input common-mode voltage range includes ground. They all exhibit excellent speed to power ratio, achieving 1 MHz of bandwidth and 1 V/ $\mu s$  slew rate with low supply current.

The LMV321 is available in the space saving 5-Pin SC70, which is approximately half the size of the 5-Pin SOT23. The small package saves space on PC boards and enables the design of small portable electronic devices. It also allows the designer to place the device closer to the signal source to reduce noise pickup and increase signal integrity.

The chips are built with Texas Instruments's advanced submicron silicon-gate BiCMOS process. The LMV321/LMV358/LMV324 have bipolar input and output stages for improved noise performance and higher output current drive.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.



These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.

**Absolute Maximum Ratings** <sup>(1)(2)</sup>

|                                                  |                          |
|--------------------------------------------------|--------------------------|
| ESD Tolerance <sup>(3)</sup>                     |                          |
| Human Body Model                                 |                          |
| LMV358/LMV324                                    | 2000V                    |
| LMV321                                           | 900V                     |
| Machine Model                                    | 100V                     |
| Differential Input Voltage                       | ±Supply Voltage          |
| Input Voltage                                    | -0.3V to +Supply Voltage |
| Supply Voltage (V <sup>+</sup> -V <sup>-</sup> ) | 5.5V                     |
| Output Short Circuit to V <sup>+</sup>           | <sup>(4)</sup>           |
| Output Short Circuit to V <sup>-</sup>           | <sup>(5)</sup>           |
| Soldering Information                            |                          |
| Infrared or Convection (30 sec)                  | 260°C                    |
| Storage Temp. Range                              | -65°C to 150°C           |
| Junction Temperature <sup>(6)</sup>              | 150°C                    |

- (1) Absolute Maximum Ratings indicate limits beyond which damage to the device may occur. Operating Ratings indicate conditions for which the device is intended to be functional, but specific performance is not guaranteed. For guaranteed specifications and the test conditions, see the Electrical Characteristics.
- (2) **If Military/Aerospace specified devices are required, please contact the Texas Instruments Sales Office / Distributors for availability and specifications.**
- (3) Human Body Model, applicable std. MIL-STD-883, Method 3015.7. Machine Model, applicable std. JESD22-A115-A (ESD MM std. of JEDEC)Field-Induced Charge-Device Model, applicable std. JESD22-C101-C (ESD FICDM std. of JEDEC)
- (4) Shorting output to V<sup>+</sup> will adversely affect reliability.
- (5) Shorting output to V<sup>-</sup> will adversely affect reliability.
- (6) The maximum power dissipation is a function of T<sub>J(MAX)</sub>, θ<sub>JA</sub>. The maximum allowable power dissipation at any ambient temperature is P<sub>D</sub> = (T<sub>J(MAX)</sub> - T<sub>A</sub>) / θ<sub>JA</sub>. All numbers apply for packages soldered directly onto a PC Board.

**Operating Ratings** <sup>(1)</sup>

|                                                      |                 |
|------------------------------------------------------|-----------------|
| Supply Voltage                                       | 2.7V to 5.5V    |
| Temperature Range <sup>(2)</sup>                     |                 |
| LMV321/LMV358/LMV324                                 | -40°C to +125°C |
| Thermal Resistance (θ <sub>JA</sub> ) <sup>(3)</sup> |                 |
| 5-pin SC70                                           | 478°C/W         |
| 5-pin SOT23                                          | 265°C/W         |
| 8-Pin SOIC                                           | 190°C/W         |
| 8-Pin MSOP                                           | 235°C/W         |
| 14-Pin SOIC                                          | 145°C/W         |
| 14-Pin TSSOP                                         | 155°C/W         |

- (1) Absolute Maximum Ratings indicate limits beyond which damage to the device may occur. Operating Ratings indicate conditions for which the device is intended to be functional, but specific performance is not guaranteed. For guaranteed specifications and the test conditions, see the Electrical Characteristics.
- (2) The maximum power dissipation is a function of T<sub>J(MAX)</sub>, θ<sub>JA</sub>. The maximum allowable power dissipation at any ambient temperature is P<sub>D</sub> = (T<sub>J(MAX)</sub> - T<sub>A</sub>) / θ<sub>JA</sub>. All numbers apply for packages soldered directly onto a PC Board.
- (3) All numbers are typical, and apply for packages soldered directly onto a PC board in still air.

## 2.7V DC Electrical Characteristics

Unless otherwise specified, all limits guaranteed for  $T_J = 25^\circ\text{C}$ ,  $V^+ = 2.7\text{V}$ ,  $V^- = 0\text{V}$ ,  $V_{\text{CM}} = 1.0\text{V}$ ,  $V_O = V^+/2$  and  $R_L > 1\text{M}\Omega$ .

| Symbol                   | Parameter                          | Conditions                                                 | Min<br>(1)  | Typ<br>(2) | Max<br>(1) | Units                        |
|--------------------------|------------------------------------|------------------------------------------------------------|-------------|------------|------------|------------------------------|
| $V_{\text{OS}}$          | Input Offset Voltage               |                                                            |             | 1.7        | 7          | mV                           |
| $\text{TCV}_{\text{OS}}$ | Input Offset Voltage Average Drift |                                                            |             | 5          |            | $\mu\text{V}/^\circ\text{C}$ |
| $I_B$                    | Input Bias Current                 |                                                            |             | 11         | 250        | nA                           |
| $I_{\text{OS}}$          | Input Offset Current               |                                                            |             | 5          | 50         | nA                           |
| CMRR                     | Common Mode Rejection Ratio        | $0\text{V} \leq V_{\text{CM}} \leq 1.7\text{V}$            | 50          | 63         |            | dB                           |
| PSRR                     | Power Supply Rejection Ratio       | $2.7\text{V} \leq V^+ \leq 5\text{V}$<br>$V_O = 1\text{V}$ | 50          | 60         |            | dB                           |
| $V_{\text{CM}}$          | Input Common-Mode Voltage Range    | For CMRR $\geq 50$ dB                                      | 0           | -0.2       |            | V                            |
|                          |                                    |                                                            |             | 1.9        | 1.7        | V                            |
| $V_O$                    | Output Swing                       | $R_L = 10\text{ k}\Omega$ to 1.35V                         | $V^+ - 100$ | $V^+ - 10$ |            | mV                           |
|                          |                                    |                                                            |             | 60         | 180        | mV                           |
| $I_S$                    | Supply Current                     | LMV321                                                     |             | 80         | 170        | $\mu\text{A}$                |
|                          |                                    | LMV358<br>Both amplifiers                                  |             | 140        | 340        | $\mu\text{A}$                |
|                          |                                    | LMV324<br>All four amplifiers                              |             | 260        | 680        | $\mu\text{A}$                |

- (1) All limits are guaranteed by testing or statistical analysis.
- (2) Typical values represent the most likely parametric norm as determined at the time of characterization. Actual typical values may vary over time and will also depend on the application and configuration. The typical values are not tested and are not guaranteed on shipped production material.

## 2.7V AC Electrical Characteristics

Unless otherwise specified, all limits guaranteed for  $T_J = 25^\circ\text{C}$ ,  $V^+ = 2.7\text{V}$ ,  $V^- = 0\text{V}$ ,  $V_{\text{CM}} = 1.0\text{V}$ ,  $V_O = V^+/2$  and  $R_L > 1\text{M}\Omega$ .

| Symbol   | Parameter                    | Conditions            | Min<br>(1) | Typ<br>(2) | Max<br>(1) | Units                                       |
|----------|------------------------------|-----------------------|------------|------------|------------|---------------------------------------------|
| GBWP     | Gain-Bandwidth Product       | $C_L = 200\text{ pF}$ |            | 1          |            | MHz                                         |
| $\Phi_m$ | Phase Margin                 |                       |            | 60         |            | Deg                                         |
| $G_m$    | Gain Margin                  |                       |            | 10         |            | dB                                          |
| $e_n$    | Input-Referred Voltage Noise | $f = 1\text{ kHz}$    |            | 46         |            | $\frac{\text{nV}}{\sqrt{\text{Hz}}}$<br>(1) |
| $i_n$    | Input-Referred Current Noise | $f = 1\text{ kHz}$    |            | 0.17       |            | $\frac{\text{pA}}{\sqrt{\text{Hz}}}$<br>(2) |

- (1) All limits are guaranteed by testing or statistical analysis.
- (2) Typical values represent the most likely parametric norm as determined at the time of characterization. Actual typical values may vary over time and will also depend on the application and configuration. The typical values are not tested and are not guaranteed on shipped production material.

### 5V DC Electrical Characteristics

Unless otherwise specified, all limits guaranteed for  $T_J = 25^\circ\text{C}$ ,  $V^+ = 5\text{V}$ ,  $V^- = 0\text{V}$ ,  $V_{\text{CM}} = 2.0\text{V}$ ,  $V_O = V^+/2$  and  $R_L > 1\text{M}\Omega$ . **Boldface** limits apply at the temperature extremes.

| Symbol                   | Parameter                          | Conditions                                                                               | Min<br>(1)                                   | Typ<br>(2) | Max<br>(1)          | Units                        |
|--------------------------|------------------------------------|------------------------------------------------------------------------------------------|----------------------------------------------|------------|---------------------|------------------------------|
| $V_{\text{OS}}$          | Input Offset Voltage               |                                                                                          |                                              | 1.7        | <b>7<br/>9</b>      | mV                           |
| $\text{TCV}_{\text{OS}}$ | Input Offset Voltage Average Drift |                                                                                          |                                              | 5          |                     | $\mu\text{V}/^\circ\text{C}$ |
| $I_{\text{B}}$           | Input Bias Current                 |                                                                                          |                                              | 15         | <b>250<br/>500</b>  | nA                           |
| $I_{\text{OS}}$          | Input Offset Current               |                                                                                          |                                              | 5          | <b>50<br/>150</b>   | nA                           |
| CMRR                     | Common Mode Rejection Ratio        | $0\text{V} \leq V_{\text{CM}} \leq 4\text{V}$                                            | 50                                           | 65         |                     | dB                           |
| PSRR                     | Power Supply Rejection Ratio       | $2.7\text{V} \leq V^+ \leq 5\text{V}$<br>$V_O = 1\text{V}$ , $V_{\text{CM}} = 1\text{V}$ | 50                                           | 60         |                     | dB                           |
| $V_{\text{CM}}$          | Input Common-Mode Voltage Range    | For CMRR $\geq 50\text{ dB}$                                                             | 0                                            | -0.2       |                     | V                            |
|                          |                                    |                                                                                          |                                              | 4.2        | 4                   | V                            |
| $A_V$                    | Large Signal Voltage Gain<br>(3)   | $R_L = 2\text{ k}\Omega$                                                                 | <b>15<br/>10</b>                             | 100        |                     | V/mV                         |
| $V_O$                    | Output Swing                       | $R_L = 2\text{ k}\Omega$ to $2.5\text{V}$                                                | $V^+ - 300$<br><b><math>V^+ - 400</math></b> | $V^+ - 40$ |                     | mV                           |
|                          |                                    | $R_L = 2\text{ k}\Omega$ to $2.5\text{V}$                                                |                                              | 120        | <b>300<br/>400</b>  |                              |
|                          |                                    | $R_L = 10\text{ k}\Omega$ to $2.5\text{V}$                                               | $V^+ - 100$<br><b><math>V^+ - 200</math></b> | $V^+ - 10$ |                     | mV                           |
|                          |                                    | $R_L = 2\text{ k}\Omega$ to $2.5\text{V}$ , $125^\circ\text{C}$                          |                                              | 65         | <b>180<br/>280</b>  |                              |
| $I_O$                    | Output Short Circuit Current       | Sourcing, $V_O = 0\text{V}$                                                              | 5                                            | 60         |                     | mA                           |
|                          |                                    | Sinking, $V_O = 5\text{V}$                                                               | 10                                           | 160        |                     |                              |
| $I_S$                    | Supply Current                     | LMV321                                                                                   |                                              | 130        | <b>250<br/>350</b>  | $\mu\text{A}$                |
|                          |                                    | LMV358 (both amps)                                                                       |                                              | 210        | <b>440<br/>615</b>  |                              |
|                          |                                    | LMV324 (all four amps)                                                                   |                                              | 410        | <b>830<br/>1160</b> |                              |

- (1) All limits are guaranteed by testing or statistical analysis.
- (2) Typical values represent the most likely parametric norm as determined at the time of characterization. Actual typical values may vary over time and will also depend on the application and configuration. The typical values are not tested and are not guaranteed on shipped production material.
- (3)  $R_L$  is connected to  $V^-$ . The output voltage is  $0.5\text{V} \leq V_O \leq 4.5\text{V}$ .

### 5V AC Electrical Characteristics

Unless otherwise specified, all limits guaranteed for  $T_J = 25^\circ\text{C}$ ,  $V^+ = 5\text{V}$ ,  $V^- = 0\text{V}$ ,  $V_{\text{CM}} = 2.0\text{V}$ ,  $V_O = V^+/2$  and  $R_L > 1\text{M}\Omega$ .

**Boldface** limits apply at the temperature extremes.

| Symbol   | Parameter                    | Conditions           | Min<br>(1) | Typ<br>(2) | Max<br>(1) | Units                                       |
|----------|------------------------------|----------------------|------------|------------|------------|---------------------------------------------|
| SR       | Slew Rate                    | (3)                  |            | 1          |            | V/ $\mu\text{s}$                            |
| GBWP     | Gain-Bandwidth Product       | $C_L = 200\text{pF}$ |            | 1          |            | MHz                                         |
| $\Phi_m$ | Phase Margin                 |                      |            | 60         |            | Deg                                         |
| $G_m$    | Gain Margin                  |                      |            | 10         |            | dB                                          |
| $e_n$    | Input-Referred Voltage Noise | $f = 1\text{kHz}$    |            | 39         |            | $\frac{\text{nV}}{\sqrt{\text{Hz}}}$<br>(3) |
| $i_n$    | Input-Referred Current Noise | $f = 1\text{kHz}$    |            | 0.21       |            | $\frac{\text{pA}}{\sqrt{\text{Hz}}}$<br>(4) |

- (1) All limits are guaranteed by testing or statistical analysis.
- (2) Typical values represent the most likely parametric norm as determined at the time of characterization. Actual typical values may vary over time and will also depend on the application and configuration. The typical values are not tested and are not guaranteed on shipped production material.
- (3) Connected as voltage follower with 3V step input. Number specified is the slower of the positive and negative slew rates.

### CONNECTION DIAGRAM




Figure 1. Top View




Figure 2. Top View










Figure 3. Top View

Devices with an asterisk (\*) are future products. Please contact the factory for availability.

Automotive Grade (Q) product incorporates enhanced manufacturing and support processes for the automotive market, including defect detection methodologies. Reliability qualification is compliant with the requirements and temperature grades defined in the AEC Q100 standard. Automotive Grade products are identified with the letter Q. Fully compliant PPAP documentation is available. For more information go to <http://www.national.com/automotive>.







### Typical Performance Characteristics

Unless otherwise specified,  $V_S = +5V$ , single supply,  $T_A = 25^\circ C$ .









**Typical Performance Characteristics (continued)**

Unless otherwise specified,  $V_S = +5V$ , single supply,  $T_A = 25^\circ C$ .









### Typical Performance Characteristics (continued)

Unless otherwise specified,  $V_S = +5V$ , single supply,  $T_A = 25^\circ C$ .



**Typical Performance Characteristics (continued)**

Unless otherwise specified,  $V_S = +5V$ , single supply,  $T_A = 25^\circ C$ .




**Typical Performance Characteristics (continued)**


Unless otherwise specified,  $V_S = +5V$ , single supply,  $T_A = 25^\circ C$ .

**Slew Rate  
vs.**


**Supply Voltage**




**Non-Inverting Large Signal Pulse Response**




**Non-Inverting Large Signal Pulse Response**




**Non-Inverting Large Signal Pulse Response**



**Non-Inverting Small Signal Pulse Response**




**Non-Inverting Small Signal Pulse Response**




**Typical Performance Characteristics (continued)**

Unless otherwise specified,  $V_S = +5V$ , single supply,  $T_A = 25^\circ C$ .


**Non-Inverting Small Signal Pulse Response**




**Inverting Large Signal Pulse Response**




**Inverting Large Signal Pulse Response**




**Inverting Large Signal Pulse Response**



**Inverting Small Signal Pulse Response**









**Inverting Small Signal Pulse Response**



### Typical Performance Characteristics (continued)


Unless otherwise specified,  $V_S = +5V$ , single supply,  $T_A = 25^\circ C$ .




**Typical Performance Characteristics (continued)**

Unless otherwise specified,  $V_S = +5V$ , single supply,  $T_A = 25^\circ C$ .


**Open Loop Output Impedance vs. Frequency**



**Short Circuit Current vs. Temperature (Sinking)**



**Short Circuit Current vs. Temperature (Sourcing)**



## APPLICATION INFORMATION

### BENEFITS OF THE LMV321/LMV358/LMV324

#### Size

The small footprints of the LMV321/LMV358/LMV324 packages save space on printed circuit boards, and enable the design of smaller electronic products, such as cellular phones, pagers, or other portable systems. The low profile of the LMV321/LMV358/LMV324 make them possible to use in PCMCIA type III cards.

#### Signal Integrity

Signals can pick up noise between the signal source and the amplifier. By using a physically smaller amplifier package, the LMV321/LMV358/LMV324 can be placed closer to the signal source, reducing noise pickup and increasing signal integrity.

#### Simplified Board Layout

These products help you to avoid using long PC traces in your PC board layout. This means that no additional components, such as capacitors and resistors, are needed to filter out the unwanted signals due to the interference between the long PC traces.

#### Low Supply Current

These devices will help you to maximize battery life. They are ideal for battery powered systems.

#### Low Supply Voltage

Texas Instruments provides guaranteed performance at 2.7V and 5V. These guarantees ensure operation throughout the battery lifetime.

#### Rail-to-Rail Output

Rail-to-rail output swing provides maximum possible dynamic range at the output. This is particularly important when operating on low supply voltages.


#### Input Includes Ground

Allows direct sensing near GND in single supply operation.

Protection should be provided to prevent the input voltages from going negative more than  $-0.3V$  (at  $25^{\circ}C$ ). An input clamp diode with a resistor to the IC input terminal can be used.

#### Ease of Use and Crossover Distortion

The LMV321/LMV358/LMV324 offer specifications similar to the familiar LM324. In addition, the new LMV321/LMV358/LMV324 effectively eliminate the output crossover distortion. The scope photos in [Figure 4](#) and [Figure 5](#) compare the output swing of the LMV324 and the LM324 in a voltage follower configuration, with  $V_S = \pm 2.5V$  and  $R_L (= 2\text{ k}\Omega)$  connected to GND. It is apparent that the crossover distortion has been eliminated in the new LMV324.



**Figure 4. Output Swing of LMV324**




Figure 5. Output Swing of LM324

### CAPACITIVE LOAD TOLERANCE

The LMV321/LMV358/LMV324 can directly drive 200 pF in unity-gain without oscillation. The unity-gain follower is the most sensitive configuration to capacitive loading. Direct capacitive loading reduces the phase margin of amplifiers. The combination of the amplifier's output impedance and the capacitive load induces phase lag. This results in either an underdamped pulse response or oscillation. To drive a heavier capacitive load, the circuit in Figure 6 can be used.




Figure 6. Indirectly Driving a Capacitive Load Using Resistive Isolation

In Figure 6, the isolation resistor  $R_{ISO}$  and the load capacitor  $C_L$  form a pole to increase stability by adding more phase margin to the overall system. The desired performance depends on the value of  $R_{ISO}$ . The bigger the  $R_{ISO}$  resistor value, the more stable  $V_{OUT}$  will be. Figure 7 is an output waveform of Figure 6 using 620Ω for  $R_{ISO}$  and 510 pF for  $C_L$ .




Figure 7. Pulse Response of the LMV324 Circuit in Figure 6

The circuit in Figure 8 is an improvement to the one in Figure 6 because it provides DC accuracy as well as AC stability. If there were a load resistor in Figure 6, the output would be voltage divided by  $R_{ISO}$  and the load resistor. Instead, in Figure 8,  $R_F$  provides the DC accuracy by using feed-forward techniques to connect  $V_{IN}$  to  $R_L$ . Caution is needed in choosing the value of  $R_F$  due to the input bias current of the LMV321/LMV358/LMV324.  $C_F$  and  $R_{ISO}$  serve to counteract the loss of phase margin by feeding the high frequency component of the output signal back to the amplifier's inverting input, thereby preserving phase margin in the overall feedback loop. Increased capacitive drive is possible by increasing the value of  $C_F$ . This in turn will slow down the pulse response.




Figure 8. Indirectly Driving A Capacitive Load with DC Accuracy

**INPUT BIAS CURRENT CANCELLATION**

The LMV321/LMV358/LMV324 family has a bipolar input stage. The typical input bias current of LMV321/LMV358/LMV324 is 15 nA with 5V supply. Thus a 100 kΩ input resistor will cause 1.5 mV of error voltage. By balancing the resistor values at both inverting and non-inverting inputs, the error caused by the amplifier's input bias current will be reduced. The circuit in Figure 9 shows how to cancel the error caused by input bias current.





Figure 9. Cancelling the Error Caused by Input Bias Current

**TYPICAL SINGLE-SUPPLY APPLICATION CIRCUITS**

**Difference Amplifier**

The difference amplifier allows the subtraction of two voltages or, as a special case, the cancellation of a signal common to two inputs. It is useful as a computational amplifier, in making a differential to single-ended conversion or in rejecting a common mode signal.



$$V_{OUT} = \left( \frac{R1 + R2}{R3 + R4} \right) \frac{R4}{R1} V_2 - \frac{R2}{R1} V_1 + \left( \frac{R1 + R2}{R3 + R4} \right) \frac{R3}{R1} \cdot \frac{V^+}{2}$$

for  $R1 = R3$  and  $R2 = R4$

$$V_{OUT} = \frac{R2}{R1} (V_2 - V_1) + \frac{V^+}{2}$$


**Figure 10. Difference Amplifier**

**Instrumentation Circuits**

The input impedance of the previous difference amplifier is set by the resistors  $R_1$ ,  $R_2$ ,  $R_3$ , and  $R_4$ . To eliminate the problems of low input impedance, one way is to use a voltage follower ahead of each input as shown in the following two instrumentation amplifiers.

**Three-Op-Amp Instrumentation Amplifier**

The quad LMV324 can be used to build a three-op-amp instrumentation amplifier as shown in [Figure 11](#).




**Figure 11. Three-Op-Amp Instrumentation Amplifier**

The first stage of this instrumentation amplifier is a differential-input, differential-output amplifier, with two voltage followers. These two voltage followers assure that the input impedance is over 100 MΩ. The gain of this instrumentation amplifier is set by the ratio of  $R_2/R_1$ .  $R_3$  should equal  $R_1$ , and  $R_4$  equal  $R_2$ . Matching of  $R_3$  to  $R_1$  and  $R_4$  to  $R_2$  affects the CMRR. For good CMRR over temperature, low drift resistors should be used. Making  $R_4$  slightly smaller than  $R_2$  and adding a trim pot equal to twice the difference between  $R_2$  and  $R_4$  will allow the CMRR to be adjusted for optimum performance.

**Two-Op-Amp Instrumentation Amplifier**

A two-op-amp instrumentation amplifier can also be used to make a high-input-impedance DC differential amplifier ([Figure 12](#)). As in the three-op-amp circuit, this instrumentation amplifier requires precise resistor matching for good CMRR.  $R_4$  should equal  $R_1$  and,  $R_3$  should equal  $R_2$ .



$$V_O = \left(1 + \frac{R_4}{R_3}\right)(V_2 - V_1), \text{ where } R_1 = R_4 \text{ and } R_2 = R_3$$


$$\text{As shown: } V_O = 2(V_2 - V_1)$$

**Figure 12. Two-Op-Amp Instrumentation Amplifier**

**Single-Supply Inverting Amplifier**

There may be cases where the input signal going into the amplifier is negative. Because the amplifier is operating in single supply voltage, a voltage divider using R<sub>3</sub> and R<sub>4</sub> is implemented to bias the amplifier so the input signal is within the input common-mode voltage range of the amplifier. The capacitor C<sub>1</sub> is placed between the inverting input and resistor R<sub>1</sub> to block the DC signal going into the AC signal source, V<sub>IN</sub>. The values of R<sub>1</sub> and C<sub>1</sub> affect the cutoff frequency,  $f_c = 1/2\pi R_1 C_1$ .

As a result, the output signal is centered around mid-supply (if the voltage divider provides V<sup>+</sup>/2 at the non-inverting input). The output can swing to both rails, maximizing the signal-to-noise ratio in a low voltage system.




$$V_{OUT} = -\frac{R_2}{R_1} V_{IN}$$

**Figure 13. Single-Supply Inverting Amplifier**

**ACTIVE FILTER**

**Simple Low-Pass Active Filter**

The simple low-pass filter is shown in [Figure 14](#). Its low-frequency gain ( $\omega \rightarrow 0$ ) is defined by  $-R_3/R_1$ . This allows low-frequency gains other than unity to be obtained. The filter has a  $-20$  dB/decade roll-off after its corner frequency  $f_c$ . R<sub>2</sub> should be chosen equal to the parallel combination of R<sub>1</sub> and R<sub>3</sub> to minimize errors due to bias current. The frequency response of the filter is shown in [Figure 15](#).



$$A_L = -\frac{R_3}{R_1}$$

$$f_c = \frac{1}{2\pi R_3 C_1}$$

$$R_2 = R_1 \parallel R_3$$

Figure 14. Simple Low-Pass Active Filter




Figure 15. Frequency Response of Simple Low-Pass Active Filter in Figure 11

Note that the single-op-amp active filters are used in the applications that require low quality factor,  $Q (\leq 10)$ , low frequency ( $\leq 5$  kHz), and low gain ( $\leq 10$ ), or a small value for the product of gain times  $Q (\leq 100)$ . The op amp should have an open loop voltage gain at the highest frequency of interest at least 50 times larger than the gain of the filter at this frequency. In addition, the selected op amp should have a slew rate that meets the following requirement:

$$\text{Slew Rate} \geq 0.5 \times (\omega_H V_{OPP}) \times 10^{-6} \text{ V}/\mu\text{sec} \quad (5)$$

where  $\omega_H$  is the highest frequency of interest, and  $V_{OPP}$  is the output peak-to-peak voltage.

### Sallen-Key 2nd-Order Active Low-Pass Filter

The Sallen-Key 2nd-order active low-pass filter is illustrated in Figure 16. The DC gain of the filter is expressed as

$$A_{LP} = \frac{R_3}{R_4} + 1 \quad (6)$$

Its transfer function is

$$\frac{V_{OUT}}{V_{IN}}(S) = \frac{\frac{1}{C_1 C_2 R_1 R_2} A_{LP}}{S^2 + S \left( \frac{1}{C_1 R_1} + \frac{1}{C_1 R_2} + \frac{1}{C_2 R_2} - \frac{A_{LP}}{C_2 R_2} \right) + \frac{1}{C_1 C_2 R_1 R_2}} \quad (7)$$




Figure 16. Sallen-Key 2nd-Order Active Low-Pass Filter

The following paragraphs explain how to select values for  $R_1$ ,  $R_2$ ,  $R_3$ ,  $R_4$ ,  $C_1$ , and  $C_2$  for given filter requirements, such as  $A_{LP}$ ,  $Q$ , and  $f_c$ .

The standard form for a 2nd-order low pass filter is

$$\frac{V_{OUT}}{V_{IN}}(S) = \frac{A_{LP} \omega_c^2}{S^2 + \left( \frac{\omega_c}{Q} \right) S + \omega_c^2} \quad (8)$$

where

Q: Pole Quality Factor

$\omega_c$ : Corner Frequency

A comparison between Equation 7 and Equation 8 yields

$$\omega_c^2 = \frac{1}{C_1 C_2 R_1 R_2} \quad (9)$$

$$\frac{\omega_c}{Q} = \frac{1}{C_1 R_1} + \frac{1}{C_1 R_2} + \frac{1}{C_2 R_2} - \frac{A_{LP}}{C_2 R_2} \quad (10)$$

To reduce the required calculations in filter design, it is convenient to introduce normalization into the components and design parameters. To normalize, let  $\omega_c = \omega_n = 1$  rad/s, and  $C_1 = C_2 = C_n = 1$  F, and substitute these values into Equation 9 and Equation 10. From Equation 9, we obtain

$$R_1 = \frac{1}{R_2} \quad (11)$$

From Equation 10, we obtain

$$R_2 = \frac{1 \pm \sqrt{1 - 4Q^2(2 - A_{LP})}}{2Q} \quad (12)$$

For minimum DC offset,  $V^+ = V^-$ , the resistor values at both inverting and non-inverting inputs should be equal, which means

$$R_1 + R_2 = \frac{R_3 R_4}{R_3 + R_4} \quad (13)$$

From [Equation 6](#) and [Equation 13](#), we obtain

$$R_3 = (R_1 + R_2)A_{LP} \quad (14)$$

$$R_4 = \left( \frac{A_{LP}}{A_{LP}-1} \right) (R_1 + R_2) \quad (15)$$

The values of  $C_1$  and  $C_2$  are normally close to or equal to

$$C = \frac{10}{f_c} \mu\text{F} \quad (16)$$

As a design example:

Require:  $A_{LP} = 2$ ,  $Q = 1$ ,  $f_c = 1$  kHz

Start by selecting  $C_1$  and  $C_2$ . Choose a standard value that is close to

$$C = \frac{10}{f_c} \mu\text{F} \quad (17)$$

$$C_1 = C_2 = \frac{10}{1 \times 10^3} \mu\text{F} = 0.01 \mu\text{F} \quad (18)$$

From [Equation 11](#) [Equation 12](#) [Equation 14](#) [Equation 15](#),

$$R_1 = 1\Omega \quad (19)$$

$$R_2 = 1\Omega \quad (20)$$

$$R_3 = 4\Omega \quad (21)$$

$$R_4 = 4\Omega \quad (22)$$

The above resistor values are normalized values with  $\omega_n = 1$  rad/s and  $C_1 = C_2 = C_n = 1\text{F}$ . To scale the normalized cutoff frequency and resistances to the real values, two scaling factors are introduced, frequency scaling factor ( $k_f$ ) and impedance scaling factor ( $k_m$ ).

$$k_f = \frac{\omega_c}{\omega_n} = \frac{2\pi \times 1 \times 10^3}{1} = 2\pi \times 10^3$$

$$k_m k_f = \frac{C_n}{C_1}$$

$$k_m = 1.59 \times 10^4 \quad (23)$$

Scaled values:

$$R_2 = R_1 = 15.9 \text{ k}\Omega \quad (24)$$

$$R_3 = R_4 = 63.6 \text{ k}\Omega \quad (25)$$

$$C_1 = C_2 = 0.01 \mu\text{F} \quad (26)$$

An adjustment to the scaling may be made in order to have realistic values for resistors and capacitors. The actual value used for each component is shown in the circuit.

## 2nd-Order High Pass Filter

A 2nd-order high pass filter can be built by simply interchanging those frequency selective components ( $R_1$ ,  $R_2$ ,  $C_1$ ,  $C_2$ ) in the Sallen-Key 2nd-order active low pass filter. As shown in [Figure 17](#), resistors become capacitors, and capacitors become resistors. The resulted high pass filter has the same corner frequency and the same maximum gain as the previous 2nd-order low pass filter if the same components are chosen.




Figure 17. Sallen-Key 2nd-Order Active High-Pass Filter

**State Variable Filter**

A state variable filter requires three op amps. One convenient way to build state variable filters is with a quad op amp, such as the LMV324 (Figure 18).

This circuit can simultaneously represent a low-pass filter, high-pass filter, and bandpass filter at three different outputs. The equations for these functions are listed below. It is also called "Bi-Quad" active filter as it can produce a transfer function which is quadratic in both numerator and denominator.




Figure 18. State Variable Active Filter

$$\begin{aligned}
 V_{LP} &= \left( \frac{2R_3}{R_2 + R_3} \right) \frac{\frac{1}{R^2 C^2}}{S^2 + \frac{1}{\left( \frac{R_2 + R_3}{2R_2} \right) RC} S + \frac{1}{R^2 C^2}} V_{IN} \\
 V_{HP} &= \left( \frac{2R_3}{R_2 + R_3} \right) \frac{S^2}{S^2 + \frac{1}{\left( \frac{R_2 + R_3}{2R_2} \right) RC} S + \frac{1}{R^2 C^2}} V_{IN} \\
 V_{BP} &= \left( \frac{2R_3}{R_2 + R_3} \right) \frac{\left( \frac{1}{RC} \right) S}{S^2 + \frac{1}{\left( \frac{R_2 + R_3}{2R_2} \right) RC} S + \frac{1}{R^2 C^2}} V_{IN}
 \end{aligned} \tag{27}$$

where for all three filters,

$$Q = \frac{R_2 + R_3}{2R_2} \tag{28}$$

$$\omega_0 = \frac{1}{RC} \quad (\text{resonant frequency}) \tag{29}$$

A design example for a bandpass filter is shown below:

Assume the system design requires a bandpass filter with  $f_o = 1$  kHz and  $Q = 50$ . What needs to be calculated are capacitor and resistor values.

First choose convenient values for  $C_1$ ,  $R_1$  and  $R_2$ :

$$C_1 = 1200 \text{ pF} \tag{30}$$

$$2R_2 = R_1 = 30 \text{ k}\Omega \tag{31}$$

Then from [Equation 28](#),

$$R_3 = R_2 (2Q - 1)$$

$$\begin{aligned}
 R_3 &= 15 \text{ k}\Omega \times (2 \times 50 - 1) \\
 &= 1.5 \text{ M}\Omega
 \end{aligned} \tag{32}$$

From [Equation 29](#),


$$R = \frac{1}{\omega_0 C_1}$$

$$\begin{aligned}
 R &= \frac{1}{(2\pi \times 10^3)(1.2 \times 10^{-9})} \\
 &= 132.7 \text{ k}\Omega
 \end{aligned} \tag{33}$$

From the above calculated values, the midband gain is  $H_0 = R_3/R_2 = 100$  (40 dB). The nearest 5% standard values have been added to [Figure 18](#).

## PULSE GENERATORS AND OSCILLATORS

A pulse generator is shown in Figure 19. Two diodes have been used to separate the charge and discharge paths to capacitor C.



**Figure 19. Pulse Generator**

When the output voltage  $V_O$  is first at its high,  $V_{OH}$ , the capacitor C is charged toward  $V_{OH}$  through  $R_2$ . The voltage across C rises exponentially with a time constant  $\tau = R_2C$ , and this voltage is applied to the inverting input of the op amp. Meanwhile, the voltage at the non-inverting input is set at the positive threshold voltage ( $V_{TH+}$ ) of the generator. The capacitor voltage continually increases until it reaches  $V_{TH+}$ , at which point the output of the generator will switch to its low,  $V_{OL}$  which 0V is in this case. The voltage at the non-inverting input is switched to the negative threshold voltage ( $V_{TH-}$ ) of the generator. The capacitor then starts to discharge toward  $V_{OL}$  exponentially through  $R_1$ , with a time constant  $\tau = R_1C$ . When the capacitor voltage reaches  $V_{TH-}$ , the output of the pulse generator switches to  $V_{OH}$ . The capacitor starts to charge, and the cycle repeats itself.




Figure 20. Waveforms of the Circuit in Figure 16

As shown in the waveforms in Figure 20, the pulse width ( $T_1$ ) is set by  $R_2$ ,  $C$  and  $V_{OH}$ , and the time between pulses ( $T_2$ ) is set by  $R_1$ ,  $C$  and  $V_{OL}$ . This pulse generator can be made to have different frequencies and pulse width by selecting different capacitor value and resistor values.

Figure 21 shows another pulse generator, with separate charge and discharge paths. The capacitor is charged through  $R_1$  and is discharged through  $R_2$ .




Figure 21. Pulse Generator

Figure 22 is a squarewave generator with the same path for charging and discharging the capacitor.




Figure 22. Squarewave Generator

### CURRENT SOURCE AND SINK

The LMV321/LMV358/LMV324 can be used in feedback loops which regulate the current in external PNP transistors to provide current sources or in external NPN transistors to provide current sinks.

#### Fixed Current Source

A multiple fixed current source is shown in Figure 23. A voltage ( $V_{REF} = 2V$ ) is established across resistor  $R_3$  by the voltage divider ( $R_3$  and  $R_4$ ). Negative feedback is used to cause the voltage drop across  $R_1$  to be equal to  $V_{REF}$ . This controls the emitter current of transistor  $Q_1$  and if we neglect the base current of  $Q_1$  and  $Q_2$ , essentially this same current is available out of the collector of  $Q_1$ .

Large input resistors can be used to reduce current loss and a Darlington connection can be used to reduce errors due to the  $\beta$  of  $Q_1$ .

The resistor,  $R_2$ , can be used to scale the collector current of  $Q_2$  either above or below the 1 mA reference value.




Figure 23. Fixed Current Source

### High Compliance Current Sink

A current sink circuit is shown in Figure 24. The circuit requires only one resistor ( $R_E$ ) and supplies an output current which is directly proportional to this resistor value.




Figure 24. High Compliance Current Sink

### POWER AMPLIFIER

A power amplifier is illustrated in Figure 25. This circuit can provide a higher output current because a transistor follower is added to the output of the op amp.




Figure 25. Power Amplifier

### LED DRIVER

The LMV321/LMV358/LMV324 can be used to drive an LED as shown in Figure 26.




Figure 26. LED Driver

### COMPARATOR WITH HYSTERESIS

The LMV321/LMV358/LMV324 can be used as a low power comparator. Figure 27 shows a comparator with hysteresis. The hysteresis is determined by the ratio of the two resistors.

$$V_{TH+} = V_{REF}/(1+R_1/R_2)+V_{OH}/(1+R_2/R_1) \tag{34}$$

$$V_{TH-} = V_{REF}/(1+R_1/R_2)+V_{OL}/(1+R_2/R_1) \tag{35}$$

$$V_H = (V_{OH}-V_{OL})/(1+R_2/R_1) \tag{36}$$

where

$V_{TH+}$ : Positive Threshold Voltage

$V_{TH-}$ : Negative Threshold Voltage

$V_{OH}$ : Output Voltage at High

$V_{OL}$ : Output Voltage at Low

$V_H$ : Hysteresis Voltage

Since LMV321/LMV358/LMV324 have rail-to-rail output, the  $(V_{OH}-V_{OL})$  is equal to  $V_S$ , which is the supply voltage.

$$V_H = V_S/(1+R_2/R_1) \tag{37}$$

The differential voltage at the input of the op amp should not exceed the specified absolute maximum ratings. For real comparators that are much faster, we recommend you use Texas Instruments's LMV331/LMV93/LMV339, which are single, dual and quad general purpose comparators for low voltage operation.




Figure 27. Comparator with Hysteresis

**PACKAGING INFORMATION**

| Orderable Device | Status<br>(1) | Package Type | Package Drawing | Pins | Package Qty | Eco Plan<br>(2)         | Lead/Ball Finish | MSL Peak Temp<br>(3) | Samples<br>(Requires Login) |
|------------------|---------------|--------------|-----------------|------|-------------|-------------------------|------------------|----------------------|-----------------------------|
| LMV321M5         | ACTIVE        | SOT-23       | DBV             | 5    | 1000        | TBD                     | CU SNPB          | Level-1-260C-UNLIM   |                             |
| LMV321M5/NOPB    | ACTIVE        | SOT-23       | DBV             | 5    | 1000        | Green (RoHS & no Sb/Br) | Call TI          | Level-1-260C-UNLIM   |                             |
| LMV321M5X        | ACTIVE        | SOT-23       | DBV             | 5    | 3000        | TBD                     | CU SNPB          | Level-1-260C-UNLIM   |                             |
| LMV321M5X/NOPB   | ACTIVE        | SOT-23       | DBV             | 5    | 3000        | Green (RoHS & no Sb/Br) | Call TI          | Level-1-260C-UNLIM   |                             |
| LMV321M7         | ACTIVE        | SC70         | DCK             | 5    | 1000        | TBD                     | CU SNPB          | Level-1-260C-UNLIM   |                             |
| LMV321M7/NOPB    | ACTIVE        | SC70         | DCK             | 5    | 1000        | Green (RoHS & no Sb/Br) | CU SN            | Level-1-260C-UNLIM   |                             |
| LMV321M7X        | ACTIVE        | SC70         | DCK             | 5    | 3000        | TBD                     | CU SNPB          | Level-1-260C-UNLIM   |                             |
| LMV321M7X/NOPB   | ACTIVE        | SC70         | DCK             | 5    | 3000        | Green (RoHS & no Sb/Br) | CU SN            | Level-1-260C-UNLIM   |                             |
| LMV324M          | ACTIVE        | SOIC         | D               | 14   | 55          | TBD                     | CU SNPB          | Level-1-235C-UNLIM   |                             |
| LMV324M/NOPB     | ACTIVE        | SOIC         | D               | 14   | 55          | Green (RoHS & no Sb/Br) | CU SN            | Level-1-260C-UNLIM   |                             |
| LMV324MT         | ACTIVE        | TSSOP        | PW              | 14   | 94          | TBD                     | CU SNPB          | Level-1-260C-UNLIM   |                             |
| LMV324MT/NOPB    | ACTIVE        | TSSOP        | PW              | 14   | 94          | Green (RoHS & no Sb/Br) | CU SN            | Level-1-260C-UNLIM   |                             |
| LMV324MTX        | ACTIVE        | TSSOP        | PW              | 14   | 2500        | TBD                     | CU SNPB          | Level-1-260C-UNLIM   |                             |
| LMV324MTX/NOPB   | ACTIVE        | TSSOP        | PW              | 14   | 2500        | Green (RoHS & no Sb/Br) | CU SN            | Level-1-260C-UNLIM   |                             |
| LMV324MX         | ACTIVE        | SOIC         | D               | 14   | 2500        | TBD                     | CU SNPB          | Level-1-235C-UNLIM   |                             |
| LMV324MX/NOPB    | ACTIVE        | SOIC         | D               | 14   | 2500        | Green (RoHS & no Sb/Br) | CU SN            | Level-1-260C-UNLIM   |                             |
| LMV358M          | ACTIVE        | SOIC         | D               | 8    | 95          | TBD                     | CU SNPB          | Level-1-235C-UNLIM   |                             |
| LMV358M/NOPB     | ACTIVE        | SOIC         | D               | 8    | 95          | Green (RoHS & no Sb/Br) | CU SN            | Level-1-260C-UNLIM   |                             |
| LMV358MM         | ACTIVE        | VSSOP        | DGK             | 8    | 1000        | TBD                     | CU SNPB          | Level-1-260C-UNLIM   |                             |
| LMV358MM/NOPB    | ACTIVE        | VSSOP        | DGK             | 8    | 1000        | Green (RoHS & no Sb/Br) | CU SN            | Level-1-260C-UNLIM   |                             |
| LMV358MMX        | ACTIVE        | VSSOP        | DGK             | 8    | 3500        | TBD                     | CU SNPB          | Level-1-260C-UNLIM   |                             |
| LMV358MMX/NOPB   | ACTIVE        | VSSOP        | DGK             | 8    | 3500        | Green (RoHS & no Sb/Br) | CU SN            | Level-1-260C-UNLIM   |                             |

| Orderable Device | Status<br>(1) | Package Type | Package Drawing | Pins | Package Qty | Eco Plan<br>(2)         | Lead/Ball Finish | MSL Peak Temp<br>(3) | Samples<br>(Requires Login) |
|------------------|---------------|--------------|-----------------|------|-------------|-------------------------|------------------|----------------------|-----------------------------|
| LMV358MX         | ACTIVE        | SOIC         | D               | 8    | 2500        | TBD                     | CU SNPB          | Level-1-235C-UNLIM   |                             |
| LMV358MX/NOPB    | ACTIVE        | SOIC         | D               | 8    | 2500        | Green (RoHS & no Sb/Br) | CU SN            | Level-1-260C-UNLIM   |                             |

(1) The marketing status values are defined as follows:

**ACTIVE:** Product device recommended for new designs.

**LIFEBUY:** TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

**NRND:** Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

**PREVIEW:** Device has been announced but is not in production. Samples may or may not be available.

**OBSELETE:** TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check <http://www.ti.com/productcontent> for the latest availability information and additional product content details.

**TBD:** The Pb-Free/Green conversion plan has not been defined.

**Pb-Free (RoHS):** TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.



**Pb-Free (RoHS Exempt):** This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

**Green (RoHS & no Sb/Br):** TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

(3) MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.


**Important Information and Disclaimer:** The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

**TAPE AND REEL INFORMATION**

**QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE**


\*All dimensions are nominal

| Device         | Package Type | Package Drawing | Pins | SPQ  | Reel Diameter (mm) | Reel Width W1 (mm) | A0 (mm) | B0 (mm) | K0 (mm) | P1 (mm) | W (mm) | Pin1 Quadrant |
|----------------|--------------|-----------------|------|------|--------------------|--------------------|---------|---------|---------|---------|--------|---------------|
| LMV321M5       | SOT-23       | DBV             | 5    | 1000 | 178.0              | 8.4                | 3.2     | 3.2     | 1.4     | 4.0     | 8.0    | Q3            |
| LMV321M5/NOPB  | SOT-23       | DBV             | 5    | 1000 | 178.0              | 8.4                | 3.2     | 3.2     | 1.4     | 4.0     | 8.0    | Q3            |
| LMV321M5X      | SOT-23       | DBV             | 5    | 3000 | 178.0              | 8.4                | 3.2     | 3.2     | 1.4     | 4.0     | 8.0    | Q3            |
| LMV321M5X/NOPB | SOT-23       | DBV             | 5    | 3000 | 178.0              | 8.4                | 3.2     | 3.2     | 1.4     | 4.0     | 8.0    | Q3            |
| LMV321M7       | SC70         | DCK             | 5    | 1000 | 178.0              | 8.4                | 2.25    | 2.45    | 1.2     | 4.0     | 8.0    | Q3            |
| LMV321M7/NOPB  | SC70         | DCK             | 5    | 1000 | 178.0              | 8.4                | 2.25    | 2.45    | 1.2     | 4.0     | 8.0    | Q3            |
| LMV321M7X      | SC70         | DCK             | 5    | 3000 | 178.0              | 8.4                | 2.25    | 2.45    | 1.2     | 4.0     | 8.0    | Q3            |
| LMV321M7X/NOPB | SC70         | DCK             | 5    | 3000 | 178.0              | 8.4                | 2.25    | 2.45    | 1.2     | 4.0     | 8.0    | Q3            |
| LMV324MTX      | TSSOP        | PW              | 14   | 2500 | 330.0              | 12.4               | 6.95    | 8.3     | 1.6     | 8.0     | 12.0   | Q1            |
| LMV324MTX/NOPB | TSSOP        | PW              | 14   | 2500 | 330.0              | 12.4               | 6.95    | 8.3     | 1.6     | 8.0     | 12.0   | Q1            |
| LMV324MX       | SOIC         | D               | 14   | 2500 | 330.0              | 16.4               | 6.5     | 9.35    | 2.3     | 8.0     | 16.0   | Q1            |
| LMV324MX/NOPB  | SOIC         | D               | 14   | 2500 | 330.0              | 16.4               | 6.5     | 9.35    | 2.3     | 8.0     | 16.0   | Q1            |
| LMV358MM       | VSSOP        | DGK             | 8    | 1000 | 178.0              | 12.4               | 5.3     | 3.4     | 1.4     | 8.0     | 12.0   | Q1            |
| LMV358MM/NOPB  | VSSOP        | DGK             | 8    | 1000 | 178.0              | 12.4               | 5.3     | 3.4     | 1.4     | 8.0     | 12.0   | Q1            |
| LMV358MMX      | VSSOP        | DGK             | 8    | 3500 | 330.0              | 12.4               | 5.3     | 3.4     | 1.4     | 8.0     | 12.0   | Q1            |
| LMV358MMX/NOPB | VSSOP        | DGK             | 8    | 3500 | 330.0              | 12.4               | 5.3     | 3.4     | 1.4     | 8.0     | 12.0   | Q1            |
| LMV358MX       | SOIC         | D               | 8    | 2500 | 330.0              | 12.4               | 6.5     | 5.4     | 2.0     | 8.0     | 12.0   | Q1            |
| LMV358MX/NOPB  | SOIC         | D               | 8    | 2500 | 330.0              | 12.4               | 6.5     | 5.4     | 2.0     | 8.0     | 12.0   | Q1            |


**TAPE AND REEL BOX DIMENSIONS**


\*All dimensions are nominal

| Device         | Package Type | Package Drawing | Pins | SPQ  | Length (mm) | Width (mm) | Height (mm) |
|----------------|--------------|-----------------|------|------|-------------|------------|-------------|
| LMV321M5       | SOT-23       | DBV             | 5    | 1000 | 203.0       | 190.0      | 41.0        |
| LMV321M5/NOPB  | SOT-23       | DBV             | 5    | 1000 | 203.0       | 190.0      | 41.0        |
| LMV321M5X      | SOT-23       | DBV             | 5    | 3000 | 206.0       | 191.0      | 90.0        |
| LMV321M5X/NOPB | SOT-23       | DBV             | 5    | 3000 | 206.0       | 191.0      | 90.0        |
| LMV321M7       | SC70         | DCK             | 5    | 1000 | 203.0       | 190.0      | 41.0        |
| LMV321M7/NOPB  | SC70         | DCK             | 5    | 1000 | 203.0       | 190.0      | 41.0        |
| LMV321M7X      | SC70         | DCK             | 5    | 3000 | 206.0       | 191.0      | 90.0        |
| LMV321M7X/NOPB | SC70         | DCK             | 5    | 3000 | 206.0       | 191.0      | 90.0        |
| LMV324MTX      | TSSOP        | PW              | 14   | 2500 | 349.0       | 337.0      | 45.0        |
| LMV324MTX/NOPB | TSSOP        | PW              | 14   | 2500 | 349.0       | 337.0      | 45.0        |
| LMV324MX       | SOIC         | D               | 14   | 2500 | 349.0       | 337.0      | 45.0        |
| LMV324MX/NOPB  | SOIC         | D               | 14   | 2500 | 349.0       | 337.0      | 45.0        |
| LMV358MM       | VSSOP        | DGK             | 8    | 1000 | 203.0       | 190.0      | 41.0        |
| LMV358MM/NOPB  | VSSOP        | DGK             | 8    | 1000 | 203.0       | 190.0      | 41.0        |
| LMV358MMX      | VSSOP        | DGK             | 8    | 3500 | 349.0       | 337.0      | 45.0        |
| LMV358MMX/NOPB | VSSOP        | DGK             | 8    | 3500 | 349.0       | 337.0      | 45.0        |
| LMV358MX       | SOIC         | D               | 8    | 2500 | 349.0       | 337.0      | 45.0        |
| LMV358MX/NOPB  | SOIC         | D               | 8    | 2500 | 349.0       | 337.0      | 45.0        |

DBV (R-PDSO-G5)

PLASTIC SMALL-OUTLINE PACKAGE




4073253-4/K 03/2006

- NOTES:
- A. All linear dimensions are in millimeters.
  - B. This drawing is subject to change without notice.
  - C. Body dimensions do not include mold flash or protrusion. Mold flash and protrusion shall not exceed 0.15 per side.
  - D. Falls within JEDEC MO-178 Variation AA.

DCK (R-PDSO-G5)


PLASTIC SMALL-OUTLINE PACKAGE



- NOTES:
- A. All linear dimensions are in millimeters.
  - B. This drawing is subject to change without notice.
  - C. Body dimensions do not include mold flash or protrusion. Mold flash and protrusion shall not exceed 0.15 per side.
  - D. Falls within JEDEC MO-203 variation AA.

DGK (S-PDSO-G8)


PLASTIC SMALL-OUTLINE PACKAGE



- NOTES:
- A. All linear dimensions are in millimeters.
  - B. This drawing is subject to change without notice.
  - C. Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.15 per end.
  - D. Body width does not include interlead flash. Interlead flash shall not exceed 0.50 per side.
  - E. Falls within JEDEC MO-187 variation AA, except interlead flash.

D (R-PDSO-G14)

PLASTIC SMALL OUTLINE




- NOTES:
- A. All linear dimensions are in inches (millimeters).
  - B. This drawing is subject to change without notice.
  -  Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.006 (0,15) each side.
  -  Body width does not include interlead flash. Interlead flash shall not exceed 0.017 (0,43) each side.
  - E. Reference JEDEC MS-012 variation AB.

# MECHANICAL DATA

PW (R-PDSO-G14)


PLASTIC SMALL OUTLINE



- NOTES:
- A. All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M-1994.
  - B. This drawing is subject to change without notice.
  - C. Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0,15 each side.
  - D. Body width does not include interlead flash. Interlead flash shall not exceed 0,25 each side.
  - E. Falls within JEDEC MO-153

D (R-PDSO-G8)

PLASTIC SMALL OUTLINE



- NOTES:
- A. All linear dimensions are in inches (millimeters).
  - B. This drawing is subject to change without notice.
  - C. Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.006 (0,15) each side.
  - D. Body width does not include interlead flash. Interlead flash shall not exceed 0.017 (0,43) each side.
  - E. Reference JEDEC MS-012 variation AA.

## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

### Products

|                              |                                                                                      |
|------------------------------|--------------------------------------------------------------------------------------|
| Audio                        | <a href="http://www.ti.com/audio">www.ti.com/audio</a>                               |
| Amplifiers                   | <a href="http://amplifier.ti.com">amplifier.ti.com</a>                               |
| Data Converters              | <a href="http://dataconverter.ti.com">dataconverter.ti.com</a>                       |
| DLP® Products                | <a href="http://www.dlp.com">www.dlp.com</a>                                         |
| DSP                          | <a href="http://dsp.ti.com">dsp.ti.com</a>                                           |
| Clocks and Timers            | <a href="http://www.ti.com/clocks">www.ti.com/clocks</a>                             |
| Interface                    | <a href="http://interface.ti.com">interface.ti.com</a>                               |
| Logic                        | <a href="http://logic.ti.com">logic.ti.com</a>                                       |
| Power Mgmt                   | <a href="http://power.ti.com">power.ti.com</a>                                       |
| Microcontrollers             | <a href="http://microcontroller.ti.com">microcontroller.ti.com</a>                   |
| RFID                         | <a href="http://www.ti-rfid.com">www.ti-rfid.com</a>                                 |
| OMAP Applications Processors | <a href="http://www.ti.com/omap">www.ti.com/omap</a>                                 |
| Wireless Connectivity        | <a href="http://www.ti.com/wirelessconnectivity">www.ti.com/wirelessconnectivity</a> |

### Applications

|                               |                                                                                          |
|-------------------------------|------------------------------------------------------------------------------------------|
| Automotive and Transportation | <a href="http://www.ti.com/automotive">www.ti.com/automotive</a>                         |
| Communications and Telecom    | <a href="http://www.ti.com/communications">www.ti.com/communications</a>                 |
| Computers and Peripherals     | <a href="http://www.ti.com/computers">www.ti.com/computers</a>                           |
| Consumer Electronics          | <a href="http://www.ti.com/consumer-apps">www.ti.com/consumer-apps</a>                   |
| Energy and Lighting           | <a href="http://www.ti.com/energy">www.ti.com/energy</a>                                 |
| Industrial                    | <a href="http://www.ti.com/industrial">www.ti.com/industrial</a>                         |
| Medical                       | <a href="http://www.ti.com/medical">www.ti.com/medical</a>                               |
| Security                      | <a href="http://www.ti.com/security">www.ti.com/security</a>                             |
| Space, Avionics and Defense   | <a href="http://www.ti.com/space-avionics-defense">www.ti.com/space-avionics-defense</a> |
| Video and Imaging             | <a href="http://www.ti.com/video">www.ti.com/video</a>                                   |

### TI E2E Community

[e2e.ti.com](http://e2e.ti.com)